

ChemiDoc™ Pro Imaging System* With Image Lab Touch Software Version 5.0

User Guide

*For Research Use Only. Not for use in diagnostic procedures.



ChemiDoc Pro Imaging System with Image Lab Touch Software User Guide

Image Lab Touch Software Version 5.0



Technical Support Department

The Technical Support department in the U.S. is open Monday through Friday, 5:00 AM to 5:00 PM, Pacific time.

Phone: 1-800-424-6723, option 2

Email: Support@bio-rad.com (U.S./Canada Only)

For technical assistance outside the U.S. and Canada, contact your local technical support office or click the Contact Us link at www.bio-rad.com.

Legal Notices

No part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopy, recording, or any information storage or retrieval system, without permission in writing from Bio-Rad Laboratories, Inc..

Bio-Rad reserves the right to modify its products and services at any time. This guide is subject to change without notice. Although prepared to ensure accuracy, Bio-Rad assumes no liability for errors or omissions, or for any damage resulting from the application or use of this information.

Bio-Rad , ChemiDoc, and GelDoc are trademarks of Bio-Rad Laboratories, Inc., Inc. in certain jurisdictions.

All trademarks used herein are the property of their respective owner.

Copyright ©2026 by Bio-Rad Laboratories, Inc. All rights reserved.

Revision History

Document	Date	Description of Change
ChemiDoc Pro Imaging System with Image Lab Touch Software (Doc ID# 10000252408)	October 2026	Initial Release
ChemiDoc Pro Imaging System with Image Lab Touch Software (Doc ID# 10000252408)	October 2026	Update Canadian TUV regulation in the Safety and Regulatory section

Table of Contents

Revision History	3
Safety and Regulatory Compliance	11
Warranty	11
General Precautions	12
Regulatory Notices	13
Safety Alerts	13
Types of Safety Hazards	13
Levels of Potential Risk	14
Instrument Safety Warnings	16
Instrument Safety Cautions	17
Excising Bands from Samples	17
Environmental and Safe Use Requirements	18
Safety and Regulatory Compliance	19
Safety Compliance	19
Electromagnetic Compatibility (EMC)	19
EMC Warnings and Notes	19
Notice	21
Power Safety	21
Fuses	21
Chapter 1 Introduction	23
Product Features	23
Front and Side Panel Components	26
Rear and Rear Side Panel Components	27
CMOS Camera	28
Image Lab Touch Software	28
Emission Filters	28
Optional Accessories	29
Sample Trays	29
Technical Specifications	30

Chapter 2 Starting Image Lab Touch Software	33
About the Welcome Screen	33
Internet Connection Icons	34
What's in the Suitcase?	34
Interacting with the Touch Screen	35
Entering Text on the Touch Screen	35
Using the On-Screen Keyboard	36
Using the On-Screen Keypad	37
Choosing Imaging Settings	38
Locking the System	40
Unlocking the System	41
Standby Mode	42
Power LED Colors	43
Shutting Down the Imager	43
Getting Help	45
Chapter 3 Logging In to Image Lab Touch Software	47
Creating the First User Account	47
Creating a Password	48
Changing a Password	49
Removing a Password	51
Linking to Your Bio-Rad BR.io Account	52
Creating the First Administrator Account	56
Becoming an Administrator after Initial Login	57
Setting Administrator Options	57
Enabling the Diagnostic Port on the ChemiDoc Pro Imaging System	66
Restricting Access to BR.io	67
Chapter 4 Understanding the Views	69
Main Toolbar Settings	69
Camera View	71
Preview	72
Image View	73
The Image View Toolbar	74
The Gallery	75
Color Cues	77

Chapter 5 Choosing a Sample Tray	81
Applications Listed by Tray Type	83
UV/Stain-Free Tray	83
Blue Tray	83
White Tray	83
Blot Tray	86
Chapter 6 Acquiring Images	89
Placing the Sample in the Imager	90
Acquiring an Image — General Steps	90
Setting Image Type and Size	92
Choosing Image Type	92
Choosing Image Size	92
Choosing the Application	94
Renaming an Application	95
Single or Multichannel Images	97
(Multichannel) Selecting a Channel Color	97
Creating Custom Applications	99
Editing Custom Applications	101
Deleting Custom Applications	102
Adjusting the Focus Offset	103
Previewing an Image	104
Exposure Settings	105
Setting Exposure for General Gels and Blots	106
Setting Exposure for Stain-Free Gels	107
Setting Exposure Time for a Chemiluminescent Blot	108
Automatic Exposure Settings	109
Setting the Exposure Automatically for Chemiluminescent Blot Applications	110
Specifying the Region of Interest for Auto-Exposure	111
Setting the Exposure Manually for Chemiluminescent Blot Applications	113
(Single Channel) Acquiring Signal Accumulation Mode (SAM) Images	115
Acquiring SAM Images Manually	115
Expanding and Collapsing SAM Groups	117
Adjusting SAM Acquisition Settings	118
Acquiring Images Using Stain-Free SAM	118

Acquiring the Image	119
(Stain-Free Gel) Skipping Gel Activation	120
(Stain-Free Gel) Acquiring an Image after Canceling Acquisition	120
(Multichannel) Retaking an Image	121
Chapter 7 Excising Bands from Samples	123
Excising Bands on a UV/Stain-Free Tray	123
Excising Bands on a White Tray	127
Excising Bands on a Blue Tray	128
Chapter 8 Viewing Images	131
Accessing the Gallery	131
Searching for Images in the Gallery	132
Selecting and Opening Images in the Gallery	133
Sorting Images in the Gallery by Date	134
Checking Intensity Values	135
Viewing Multichannel Images in Image View	137
Viewing a Composite or Merged Image in Grayscale	139
Comparing Images	140
Copying Image Settings	142
Viewing Image Information	144
Viewing SAM Images	146
Chapter 9 Merging Images	149
Naming Merged Images	151
Chapter 10 Managing Images	153
Adding Notes to an Image File	153
Changing the File Naming Format	154
Renaming Images	156
Renaming SAM Images	157
Printing Images	159
Deleting Images	159
Deleting SAM Images	160
Chapter 11 Exporting Images	163
Automatically Exporting Images	164
Exporting Images	165

Export Formats	168
Choosing Export Formats	168
Exporting to BR.io	171
Manually Exporting Images to BR.io	171
Automatically Exporting to BR.io	172
Exporting to a USB Drive or External Hard Drive	173
Preparing to Export Images to a Shared Folder	174
Creating a Shared Folder on a Windows Computer	174
Creating a Shared Folder on a Mac Computer	177
Determining the UNC of a Previously Shared Folder	180
Determining the UNC Path to a Network Folder on a Windows Computer	180
Determining the UNC Path to a Network Folder on a Mac Computer	181
Exporting to a Shared Folder for the First Time	183
Exporting to a Shared Folder on a Network or Computer	184
Entering Log-in Credentials	184
Exporting to a Recent Location	186
Removing Network Locations	188
Disconnecting from a Shared Folder	188
Chapter 12 System Settings	189
Setting the Instrument Name	189
Instrument Standby Settings	191
Setting the System Date, Time, and Time Zone	193
Setting the System Language	198
Setting the Sound Volume	199
Configuring the Network Connection	200
Setting Up an Ethernet Connection	200
Setting Up a Wireless Connection	205
Exporting Log Files	209
Appendix A Maintaining the Imaging System	211
Updating the Software and Firmware on ChemiDoc Pro System Imagers	211
Verifying the Current Software, Firmware, and Operating Versions	211
Updating the Software and Firmware via the Internet	212
Updating the Software and Firmware via USB Drive	214
Leveling the Imager	214

Cleaning the Instrument	216
Preparing the ChemiDoc Pro Imaging System for Shipping	218
Maintaining the LED Lamps	219
Replacing the Fuses	219
Exporting Log Files	220
Appendix B Important Imaging Concepts	223
Exposure Settings for Chemiluminescent Applications	223
The Image Resolution/Time Scale	224
How Binning Settings Affect Image Quality	225
Specifying the Region of Interest for Optimal Exposure	227
Adjusting How Images Are Displayed	228
Adjusting Image Brightness and Contrast	228
Restoring Default Settings	230
(Single Channel) Signal Accumulation Mode	230
Appendix C Application Emission Filter and Excitation Source Information	233
Appendix D Free and Open-Source Notices for ChemiDoc Pro Imaging Systems	239
Appendix E Ordering Information	241

Safety and Regulatory Compliance

Note: This instrument has been tested and found to comply with the limits for a Class A digital device pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This instrument generates, uses, and can radiate radio frequency energy. If not installed and used in accordance with the instruction manual, it may cause harmful interference to radio communications. Operation of this instrument is intended for laboratory use only and if used in a residential area, is likely to cause harmful interference in which case users will be required to correct the interference at their own expense.



WARNING: Because some imaging applications involve UV illumination, the Bio-Rad imaging systems are labeled as Group 3 (High Risk) by the International Electrotechnical Commission standard IEC/EN 62471. The imaging systems should be used only by trained personnel who know the health risks associated with the UV radiation normally associated with these instruments. Users should be trained on the appropriate personal protective equipment for working with UV light to minimize UV exposure.

Warranty

The ChemiDoc Pro Imaging System is warranted against defects in materials and workmanship for one year. If any defect occurs in the instrument during this warranty period, Bio-Rad Laboratories, Inc. will repair or replace the defective parts at its discretion without charge. The following defects, however, are specifically excluded:

- Defects caused by improper operation
- Repair or modification done by anyone other than Bio-Rad Laboratories, Inc. or the company's authorized agent
- Use of spare parts supplied by anyone other than Bio-Rad Laboratories, Inc.
- Damage caused by accident or misuse
- Damage caused by disaster
- Corrosion caused by improper solvents or samples

General Precautions

- Read the user guide carefully.
- Operate the instrument only for its intended purpose.
- Connect the instrument to a grounded power source and to a circuit breaker.
- Do not pour liquids on or inside the instrument.
- Clean the sample tray after use.

Regulatory Notices

The ChemiDoc Pro System is designed and certified to meet EN 61010, the internationally accepted electrical safety standard, EMC regulations, and TUV requirements. Certified products are safe to use when operated in accordance with this user guide. Do not modify or alter these instruments in any way. Modification or alteration of these instruments will


- Void the manufacturer's warranty
- Void the regulatory certifications
- Create a potential safety hazard



Bio-Rad Laboratories, Inc. is not responsible for any injury or damage caused by use of these instruments for purposes other than those for which they are intended, or by modifications of the instruments not performed by Bio-Rad Laboratories, Inc. or an authorized agent.

South Korea

KC certification demonstrates a product's compliance with Korean safety regulations. The KC certification's primary purpose is to identify and eliminate potential hazards to the health and safety of consumers.



Safety Alerts

Alert icons appear in cautionary and warning paragraphs in this guide to call attention to safety hazards.

Types of Safety Hazards

Most alert icons depict the relevant type of safety hazard.

Table 1. Safety symbols.

Alert Icon	Explanation
	General — Indicates a potential hazard requiring special attention. This icon appears when the hazard or condition is of a general nature.
	Electrical Hazard — Indicates a potential hazard requiring special attention when you are working with electricity or electrical equipment.
	Extreme heat and flammable materials Indicates a potential hazard requiring special attention when you are working with extreme heat and flammable materials.
	Radiation hazard Indicates a potential hazard requiring special attention when you are working with UV radiation.

Levels of Potential Risk

Each alert icon appears in a paragraph type in this guide that indicates the level of potential risk posed by the hazard or action described.

Cautions

A caution (example shown below) alerts you to take or avoid a specific action that could result in loss of data or damage to the instrument. A caution can also indicate that minor or moderate injury might occur if the precaution against a potential hazard is not taken.



Caution: Refer all servicing to qualified Bio-Rad personnel or their agents.

Warnings

A warning (example shown below) precedes an action that, if not followed correctly, could cause serious injury or death to the operator, serious or total loss of data, or serious damage to the instrument.



WARNING! Radiation Hazard — Keep the UV shield open for as little time as possible.

Instrument Safety Warnings

Before operating the imaging system, carefully read the explanation for each safety icon.

Safety Icon	Explanation
	Caution: With the exception of cleaning transilluminator tray, refer all servicing to qualified Bio-Rad personnel or their agents. If you experience technical difficulties with the instrument, contact Bio-Rad to schedule service. The instrument should not be modified or altered in any way. Alteration voids the manufacturer's warranty and might create a potential safety hazard for the user.
	WARNING! The transilluminator LEDs in the ChemiDoc Pro System imager are 279 nm +/- 5 nm, which falls between UV-B (280–315 nm) and UV-C (100–280 nm) according to the World Health Organization (WHO). If any interlock is defeated, there is a possibility of UV-B or UV-C radiation hazard due to the UV light exposure. Exercise caution when servicing the instrument.
	WARNING! This instrument must be connected to an appropriate AC voltage outlet that is properly grounded.

The following warning label is also affixed to all imaging systems:



In the IEC/EN 62471 standard developed by the International Electrotechnical Commission, Group 3 is classified as High Risk, where even momentary exposure to ultraviolet light (Actinic UV (200–400 nm)) is hazardous. Specifically, when viewing around the UV shield at a distance of 20 cm, the measured Actinic UV emission is approximately 2.5 W/m², with a permissible exposure time of about 12 seconds; where even momentary exposure to Blue-light (300–700 nm) emission, when viewing without PPE at a distance of 20 cm, the measured Blue-light (300–700 nm) emission is approximately 1.5 W/m², with a permissible exposure time of about 60 seconds.

Important: Ensure anyone using the instrument wears approved personal protective equipment (PPE).

Instrument Safety Cautions

Before operating the ChemiDoc Pro System imaging system, carefully read the following cautions. These cautions are also included in the appropriate chapter of this guide.



Caution: The materials in the sample trays and transilluminator drawer have limited acidic and basic chemical resistance, which includes many Coomassie-based stains and chemiluminescent reagents. Thoroughly wipe down surfaces with deionized water and laboratory tissues if exposure to acidic or basic solutions occurs.

Excising Bands from Samples



Caution: Before you begin excising bands, ensure that you have on the required protective gear and that the UV shield is installed.



Caution: When excising bands on the UV/Stain-Free Tray, keep the UV shield open for as little time as possible.



Caution: Sharp cutting tools can easily damage the surface of the tray. To avoid this, place a sheet of clear glass or plastic on the tray before you add the gel sample. Use a *chopping* motion rather than a *sawing* motion.

Environmental and Safe Use Requirements

The imager requires a space of 50 x 45 x 64 (W x H x D) and a clearance of at least 15.5 cm from each side for instrument ventilation and for connecting or disconnecting the AC power cord. Place the imager on a sturdy and level laboratory bench or table away from excessive heat and moisture.



WARNING! Transilluminators are powerful sources of UV radiation, which can cause serious damage to unprotected eyes and skin. The accessory UV shield provides some UV protection; however, this shield does not protect others standing in the area around the imager. Specifically, when viewing around the UV shield at a distance of 20 cm, the measured Actinic UV emission is approximately 2.5 W/m², with a permissible exposure time of about 12 seconds; where even momentary exposure to Blue-light (300–700 nm) emission, when viewing without PPE at a distance of 20 cm, the measured Blue-light (300–700 nm) emission is approximately 1.5 W/m², with a permissible exposure time of about 60 seconds. Before performing band excision, the user and other lab personnel in proximity to the imager must put on protective gear including UV protective safety glasses, a face shield, lab coat, and gloves to ensure that no skin is exposed. A typical and reasonable expectation of use is three operations a day per user for three minutes each. Bystanders without protective gear must stand at least 1.5 meters (five feet) away from the imager and limit their exposure to no longer than one hour per day.

Table 2. Environment requirements for the ChemiDoc Pro System imaging system.

Parameter	Specification
Installation site	Indoor use only
Operating altitude	Up to 2,000 m above sea level
Operating voltage	100–240 VAC; 50/60 Hz; 250 W
Operating temperature	10–28°C 50–82.4°F
Operating humidity	20–80% relative humidity (noncondensing)
MAINS supply voltage fluctuations	± 10%
Overvoltage category	II
Pollution degree	2

Safety and Regulatory Compliance

Safety Compliance

The ChemiDoc Pro System has been tested and found to be in compliance with all applicable requirements of the following safety and electromagnetic standards:

- IEC61010-1:2010/AMD12016 Safety requirements for electrical equipment for measurement, control, and laboratory use, Part 1: General requirements
- IEC 62471:2006 Photobiological safety of lamps and lamp systems
- CAN/CSA-C22.2 NO. 61010-1-12:2018 Safety requirements for electrical equipment for measurement, control, and laboratory use, Part 1: General Requirements
- EN 61010-1:2010 Safety requirements for electrical equipment for measurement, control, and laboratory use, Part 1: General requirements
- UL 61010-1:2012 Safety requirements for electrical equipment for measurement, control and laboratory use — Part 1: General Requirements

Electromagnetic Compatibility (EMC)

The ChemiDoc Pro System has been tested and found to be in compliance with all applicable requirements of the following electromagnetic compatibility standards:

- IEC 61326-1:2020 Electrical equipment for measurement, control and laboratory use — EMC requirements — Part 1: General requirements. Tested as a Class A device
- FCC Part 15, Subpart B, Sections 15.107 and 15.109. Tested as a Class A digital device
- CAN ICES-001(A) / NMB-001(A) This Industrial, Scientific and Medical (ISM) device complies with Canadian ICES-001. Cet appareil ISM est conforme à la norme NMB-001 du Canada

EMC Warnings and Notes

- **Warning:** Changes or modifications to this unit, not expressly approved by Bio-Rad, could void the user's authority to operate the equipment.
- **Note:** This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications.

Operation of this equipment in a residential area is likely to cause harmful interference, in which case the user will be required to correct the interference at their own expense.

- **Note regarding FCC compliance:** Although this instrument has been tested and found to comply with Part 15, Subpart B of the FCC Rules for a Class A digital device, please note that this compliance is voluntary, for the instrument qualifies as an “exempted device” under 47 CFR 15.103 (c), in regard to the cited FCC regulations in effect at the time of manufacture.

Notice

Bio-Rad's imagers are intended for research use only and not intended for diagnostic purposes. They are intended for use by specialized personnel who know the health risks associated with reagents used in electrophoresis. The UV light source is computer controlled, and proper interlocks are implemented to avoid users' accidental exposure to UV radiation. Bio-Rad Laboratories, Inc. is not responsible for any injury or damage caused by use of these instruments for purposes other than those for which they are intended, or for instrument modifications not performed by Bio-Rad Laboratories, Inc. or an authorized agent.

Power Safety

The imager uses a universal power supply that automatically selects the correct voltage for your country or region.

Fuses

The imager has two user-serviceable fuses, F1 and F2, which are located on the rear panel and are a part of the power entry module.

Chapter 1 Introduction

The ChemiDoc Pro Imaging System (known in this guide as the ChemiDoc Pro System) facilitates high sensitivity and high quality image acquisition for a range of scientific applications. The imager uses Image Lab Touch Software to control image capture and optimization. You interact with the imager using an integrated touch screen and a simple user interface. Using Image Lab Touch Software, you can acquire and view images and fine tune their appearance. You can then export images to a computer and analyze them with Image Lab software, or export them to the Bio-Rad cloud application, BR.io and analyze them using Advanced Image Analysis..

Note: The ChemiDoc Pro System does not support image analysis. Use the Bio-Rad desktop software Image Lab Desktop Software, version 6.1 or greater on a separate computer to analyze images acquired with the imaging systems. If you have a BR.io account, and the ChemiDoc Pro System is connected to BR.io, BR.io auto-analyzes the image to show the image's gel or blot borders as well as analysis information.

The Bio-Rad imagers are compact gel/blot imaging instruments. These instruments automate the parameter selection for acquisition of high-quality and high-sensitivity gel and multichannel western blot images with the tap of an on-screen button.

Using the ChemiDoc Pro System Imaging System, you can acquire up to a four-channel image consisting of data from a chemiluminescent channel, fluorescent channel, and a colorimetric channel.

Note: This user guide includes examples of images acquired with applications available only on ChemiDoc MP Imaging Systems. The accompanying instructions are accurate for both systems.

Product Features

Bio-Rad imagers support the acquisition of images from a wide range of laboratory sample mediums. The ChemiDoc Pro System imager offers the following features:

- Excitation sources for detecting these fluorophores and dyes:
 - ☐ Trans-UV
 - ☐ Trans-Amber
 - ☐ Trans-Blue
 - ☐ Epi-UVA

- ☐ Epi-Blue
- ☐ Epi-Green
- ☐ Epi-Red
- ☐ Epi-Far Red
- ☐ Epi-IR
- Support for colorimetric western blotting applications, chemiluminescent and fluorescent imaging, as well as DNA/protein gel visualization
- Multiplex fluorescent western blotting applications
- Smart, tray-based imaging that identifies the correct applications and presents appropriate filter and illumination sources for each
- The ability to create custom applications when acquiring single or multichannel images
- Dynamic flat fielding specific to each application (except custom applications)
- Dynamic range of >4.0 orders of magnitude
- Connectivity to your company's Internet via Ethernet or Wi-Fi
- Connectivity to the BR.io cloud application via Ethernet or Wi-Fi
- The ability to auto-upload images to a location on your company's network designated by your Image Lab Touch Software Admin
- The ability to print images to the Sony UP-X898MD printer that is connected to your imager
- The ability to auto-upload images to your BR.io account and analyze them in Advanced Image Analysis

You can also download images from BR.io to your computer to analyze or view them in Image Lab desktop software.

For more information about BR.io, go to [BR.io](https://br.io). From the BR.io Home page, you can

- ☐ Create a BR.io account
- ☐ Explore the BR.io app via video
- ☐ Access helpful BR.io guides
- ☐ Review gel and blot border analysis data. BR.io auto-analyzes images after the ChemiDoc Pro System completes acquisition and sends the images to BR.io.

Linking your ChemiDoc Pro System to your BR.io account requires an Internet connection. See your IT or ChemiDoc Pro System administrator to connect your ChemiDoc Pro System imager to the Internet.


Front and Side Panel Components



LEGEND

1	Touch screen
2	USB C port
3	USB 3.0 A port
4	System on/off button
5	Transilluminator drawer handle
6	Transilluminator drawer

Rear and Rear Side Panel Components



LEGEND

1	USB C ports
2	USB 3.0 A ports
3	Ethernet port
4	System on/off switch
5	Fuse
6	AC power receptacle

USB Ports

The instrument has six USB ports:

- Use the USB 2.0 A ports on the back of the instrument to connect any of the following accessories to the imaging system:
 - ☐ Mouse
 - ☐ Wi-Fi dongle
 - ☐ Other peripherals
- Use the USB 3.0 A port on the side of the instrument to connect a USB drive to quickly copy large data files
- Use the USB 3.0 C port on the side of the instrument to connect a USB drive.

Ethernet Port

Use this port to connect the instrument to a network.

Note: The ChemiDoc Pro System imaging system cannot be controlled by an external computer.

CMOS Camera

ChemiDoc Pro System uses a moveable zoom camera and lens to acquire samples to acquire smaller or larger sample sizes. Image Lab Touch Software also crops the full-view image to obtain smaller sample sizes. Images maintain the same number of pixels regardless of sample dimensions.

Image Lab Touch Software uses a patented algorithm to acquire chemiluminescent samples. See [Technical Specifications on page 30](#) for more information.

Image Lab Touch Software

The imager ships with Image Lab Touch Software installed.

Emission Filters

The imager has a motorized emission filter for fluorescent and white light applications, which automatically moves out of its position in front of the camera lens when not required.

Optional Accessories

See [Appendix E, Ordering Information](#), for a list of optional accessories and replacement parts.

Sample Trays

Table 3. Sample trays.

Tray	Description
Blot Tray	The Blot Tray ships with the imaging system and can be used with all blotting applications.
UV/Stain-Free Tray	The UV/Stain-Free Tray ships with the imaging system. The UV/Stain-Free Tray is used for applications that utilize UV excitation sources.
White Tray	The optional White Tray is used for applications that utilize white excitation sources such as Coomassie gels or silver stained samples.
Blue Tray	The optional Blue Tray is used for applications that utilize blue excitation sources, such as StarBright 520 and StarBright 700 fluorophores and SYBR [®] Safe and GelGreen dyes.

Technical Specifications

Table 4. Technical specifications.

Supported Applications	
Fluorescence	Yes
Chemiluminescence	Yes
Colorimetry	Yes
Hardware Specifications	
Touch screen functionality	■ Multitouch capable ■ Display resolution 1920 x 1080 pixels ■ 33.78 cm (~13.3") TFT display
Onboard computer system	■ 4 GB DDR4 RAM ■ 1 TB disk space ■ 6 USB ports (3 USB 3.0 Type-A ports, 3 USB 3.0 Type-C ports)
Sample thickness	Maximum supported thickness: 5 mm
Maximum image area	■ Length: 14 cm (5.5") ■ Width: 21 cm (8.27")
Excitation source	■ Trans-UVC (standard) ■ Epi-UV (standard) ■ Epi-Blue (standard) ■ Epi-White (standard) ■ Epi-Green (standard) ■ Epi-Red (standard) ■ Epi-Far Red (standard) ■ Trans-White (standard, requires an optional White tray) ■ Trans-Blue (standard, requires an optional Blue tray)
Detector	9.07 IMX533 BSI CMOS


Table 4. Technical specifications., continued

Emission filter	■ 511/252 ■ 532/28 ■ 590/110 ■ 595/36 ■ 700/50 ■ 715/30 ■ 836/47
Dynamic range	>4.0 orders of magnitude
Pixel density (gray levels)	65,535
Instrument size	■ Depth: 45.0 cm (~18") ■ Width: 45.0 cm (~18") ■ Height: 62.5 cm (25")
Instrument weight	~39 kg (~90 lbs)
Automation Capabilities	
Workflow automated selection	Application driven, tray-based imaging and auto-selection of excitation source
Image flat fielding	Dynamic; precalibrated and optimized per application (excluding custom applications)
Autoexposure	2 user-defined modes (rapid or optimal)

Chapter 2 Starting Image Lab Touch Software

Press the On button on the imaging system. The imaging system turns on and Image Lab Touch Software starts automatically.

The Welcome screen appears.



About the Welcome Screen

On the Image Lab Touch Software Welcome screen, you can customize the text for your organization. For example, you can enter the name of your business or laboratory in the upper box and add a warning message or other helpful information in the second box. You can enter one line of text in the upper box, and you can fill the lower box with text. The box does not scroll.

To edit Welcome screen text

1. Press and hold on the text you want to change. The on-screen keyboard appears.
2. Enter your text.
3. Tap the keyboard key on the lower right to save your changes and close the keyboard. For information on the keyboard, see [Using the On-Screen Keyboard on page 36](#).

Internet Connection Icons


On the lower left corner of the Image Lab Touch Software Welcome screen the system displays one of three icons, which indicate Internet connectivity:

Table 5. Welcome screen icons.

Icon	Description
	Indicates no Internet connectivity because neither an Ethernet cable nor a Wi-Fi adapter are installed
	Indicates an Ethernet connection Note: If both an Ethernet cable and a Wi-Fi adapter are installed, the system defaults to Ethernet connection and only this symbol will appear on the Welcome screen
	Indicates a Wi-Fi connection

What's in the Suitcase?

Tapping the Suitcase in the lower right corner of the Welcome screen displays the following commands:



Service Logout — enables service personnel to access the system for maintenance and service procedures.

Level the Imager — enables the user to adjust the imager height to optimize image acquisition.

Prepare the Instrument for Shipping — guides the user through the steps to prepare the imager for shipping. For more information, see [Preparing the ChemiDoc Pro Imaging System for Shipping on page 218](#).

Interacting with the Touch Screen

In Image Lab Touch Software, you access imaging settings by tapping the setting type on the touch screen.

- Tap an imaging settings tile to open dialogs in which you can specify imaging settings.
- Tap an icon to execute a command or to open a menu or a view.
- Tap a box to display an on-screen keyboard or numeric keypad in which you can enter data.

Table 6. Touchscreen actions.

Action	Definition
Tap	Briefly touch the screen surface.
Double-tap	Tap twice quickly.
Pan	Touch and then move your finger left or right.
Swipe	Slide a finger up, down, or across a box or screen to scroll contents.
Stretch	Place a thumb and one or two fingers together on the screen, and then move them apart to zoom in.
Pinch	Place a thumb and one or two fingers slightly apart on the screen, and then move them together to zoom out.

Alternatively, you can use a USB mouse to click tiles and icons or to click in boxes, and you can enter the data with a USB keyboard.

Important: Plug in the USB mouse before you turn on the system to enable the mouse pointer to appear.

Tip: When you use a USB mouse, read the instruction *tap* in this guide as *click*.

Entering Text on the Touch Screen

You can enter or edit text in text boxes using the on-screen keyboard or keypad. You can also enter text using a USB keyboard.

To access the on-screen keyboard or keypad

- Tap in a text box.


The appropriate on-screen input device appears.

Using the On-Screen Keyboard

Text boxes appear on the screen in which you can enter or edit text.

To display the keyboard

- Tap in a box to display the on-screen keyboard.



Use the on-screen keyboard or attach a USB keyboard to the imager to enter data.

You can switch between an English language and Simplified Chinese keyboard. Tap the Globe key on the bottom left of the keyboard to change keyboards and enter English alphabetic characters, numbers and symbols, or Simplified Chinese characters.

Tip: You can change the system language to display all on-screen text in either English language or Simplified Chinese language.


Using the On-Screen Keypad

Text boxes appear on the screen in which you can enter or edit numerals or text. You can enter numerals using the on-screen numeric keypad.

To display the numeric keypad

- ▶ Tap in a box.

The keypad appears on the screen.




To use the keypad

- Tap the text box to display the range of valid values below the box.
- If a number you tap does not appear on the screen, verify that the number is within the range of valid values. Invalid numbers are not accepted. If you enter an invalid number and tap Done, the box turns red.
- Some properties are set by entering data in multiple text boxes. After you enter data in a box, tap the next box. All edits in each box are saved automatically.
- Tap Done or tap anywhere else on the screen to close the keypad.

Choosing Imaging Settings

Image Lab Touch Software displays an imaging settings tile for each channel image you want to acquire. For example, when you tap Single, Camera view displays a single imaging settings tile in the left pane:




To choose your settings


1. Tap Single or Multi to acquire a single-channel or multichannel image.



2. Tap Image Size to display image size settings and then select the image size you want.



The dimensions of the image size you select appear when you tap Image Size. Similarly, the application and exposure settings you select appear under Application and Exposure. For example, when you tap Application in the tile, application categories and application types compatible with the selected application category appear:



Locking the System

If your imaging system has an administrator and if you log in with a password, you can lock the system. This prevents other users from interrupting an acquisition or changing settings.

While the system is locked, only you (the current user) or an administrator can log you off the locked system. If an administrator chooses to log you off while an action is in progress, the action and the lock are canceled.


To lock the system during an acquisition

1. Tap Camera to start an acquisition.
2. In the progress bar that appears, tap the Lock icon in the lower right corner.


The system locks and the acquisition continues.

To lock the system at any time

- On the main toolbar, tap User Settings and then tap Lock Display.



The touch screen appears dimmed. The name of the current user and buttons for unlocking or logging off the system appear in the upper right area.



Unlocking the System

The user who locked the system (that is, the current user) can unlock it. An administrator can also unlock the system by logging off the user who created the lock. When the user is logged off, the lock is canceled, and the system is again available.

To unlock the system (current user only)

1. On the locked screen, tap Unlock.
2. Enter your password in the box that appears.

The lock is canceled and you can continue to work with the system.

Note: Users can attempt to unlock their screen up to three times. After three failed attempts, the account locks and cannot be unlocked for five minutes.

To log off the current user (administrators only)

1. On the locked screen, tap Admin Logoff.

The system prompts you to identify yourself as an administrator.

2. Enter your user name and password and tap OK.

If an action is in progress, a message notifies you that data might be lost if you log off the current user.

3. Tap Yes to log off the current user or No to cancel.

Standby Mode

Users can configure the ChemiDoc Pro System imager to enter standby mode after 5, 10, 15, or 30 minutes, or one hour of inactivity. In standby mode, the imager turns off the monitor, pulses the LED indicator next to the front power button blue, sets the cooled camera to a standby temperature, and logs out users.


The imager exits standby mode and displays the Home window when a user interacts with the touchscreen or taps the power button. If the imager is locked, the Lock screen appears with the name of the logged-in user.

Admins can configure the ChemiDoc Pro System standby timer (5, 10, 15, or 30 minutes, or one hour) in the Standby section of the Settings menu. For more information, see [Instrument Standby Settings on page 191](#)


Note: You can also enter standby mode by tapping the power button on the front of the instrument. However, you cannot enter standby mode if the instrument is acquiring an image or during a BR.io upload.

To immediately enter Standby mode

1. In the User Options menu, tap Log Out.



2. In the Confirm Log Out dialog, tap Standby.



3. The imager enters Standby mode.

Power LED Colors

The imager's power LED (located by the front power button) indicates its status with the following colors:

- **Green** — Camera is cool and ready to acquire an image
- **Green (blinking)** — Image acquisition in progress or imager is calibrating the White Tray
- **Blue (pulsating)** — Standby mode
- **White** — Imager is powering on or camera is cooling
- **White (pulsating)** — Imager is powered off using the front power button
- **Red (blinking)** — Instrument hardware error
- **Off** — Imager is excising bands, or the imager is powered off from the rear switch

Shutting Down the Imager

Important: Follow these instructions to safely and completely shut down the ChemiDoc Pro System.

To shut down the ChemiDoc Pro System

1. Ensure that the instrument is not in the process of acquiring an image.
2. Tap the power button at the front of the instrument.
3. (Optional) You can also shut down the instrument by pressing the front power button for five seconds.
4. In the Power Off dialog, tap Yes to confirm shut down.

The instrument powers off, and the LED on the front of the imager pulses white.

Note: You can also shut down the instrument using the power switch on the back of the instrument.

Getting Help

Online help is available in each main view and in selected dialogs.

To access help

- Tap the question mark icon in the main toolbar to open the help topic for the current screen.
- Scroll to display longer topics and to access links to related topics.
- Tap Help Topics at the bottom of any help topic to view a list of all main help topics.
- Tap the Quick Help icon () for short descriptions of each of the display's features.

To close Help

- ▶ Tap the X in the upper right corner of the topic.

Chapter 3 Logging In to Image Lab Touch Software

The first user to start Image Lab Touch Software on the instrument must create either a personal user or administrator account. The software prompts you to indicate whether you want to create an administrator account.

After the first person creates the first account, subsequent users can log into a general user account or create a personal user account. After the first administrator account is created, only the administrator can assign the administrator account to other users.

Important: Until an administrator is designated, all user accounts have administrative privileges.

This chapter explains how to create the first accounts in Image Lab Touch Software.

Creating the First User Account

The first time you run Image Lab Touch Software, you must enter a user name to log in. The software prompts the first user to choose whether the account will be an administrator.

Note: This section explains how to create the first user account the first time you run Image Lab Touch Software. For information about creating the first administrator account when you first run Image Lab Touch Software, see [Creating the First Administrator Account on page 56](#).

To create the first user account

1. Tap anywhere in the Welcome screen.

The login dialog appears.

A screenshot of a login dialog box. It features a rectangular text input field with the placeholder text "Enter user name". To the right of the text field is a button with an orange plus sign icon and the word "Create" written below it.

2. Tap inside the text box.
3. Using the on-screen keyboard that appears, tap in a user name and then tap Create.

Note: Names cannot contain the characters \ / : * ? " < . | or start or end with a space.

The system prompts you to choose whether you want to be an administrator and displays information that helps you decide.

4. Tap No.

Image Lab Touch Software opens to the default view.


Creating a Password

After an administrator has been appointed, the administrator can require users to log in with a password and set other options to ensure system security. Administrators always log in with a password. Passwords must be 6–32 characters long and contain at least one of each of the following:

- Uppercase letter
- Lowercase letter
- Number
- Special character

To create a password

1. Tap User Settings in the main toolbar.



2. Tap Create Password. The Create password dialog appears.

A screenshot of the 'Create Password (required)' dialog box. The dialog has a title bar with a close button (X). It contains two input fields: 'New password' and 'Confirm password', each with a toggle icon (eye) to the right. Below the fields, there is a text instruction: 'Passwords must be 6 to 32 characters and contain one uppercase letter, one lowercase letter, one number, and one special character.' At the bottom right, there are two buttons: 'OK' and 'Cancel'.


3. Tap New password.

4. Type a password using the on-screen keyboard.
5. In the Confirm password box, enter the password again.
6. Tap OK.

Changing a Password

To change a password

1. Tap User Settings in the main toolbar.



2. Tap Change Password.

The Change password dialog appears.

A screenshot of a 'Change Password' dialog box. The dialog has a title bar with the text 'Change Password' and a close button (X). It contains three input fields: 'Current password', 'New password', and 'Confirm password'. Each field has an eye icon to its right, indicating a toggle for password visibility. Below the input fields, there is a text block providing password requirements: 'Passwords must be 6 to 32 characters and contain one uppercase letter, one lowercase letter, one number, and one special character. Password may be blank if passwords are not required.' At the bottom right of the dialog, there are two buttons: 'OK' and 'Cancel'.

3. Tap Current password.
4. Type your current password using the on-screen keyboard.
5. Enter a new password in the New password box.
- Note:** You cannot reuse any of your last five passwords.
6. Enter the new password again in the Confirm password box.

7. Tap OK.

Removing a Password

If no administrator has been assigned, or if the administrator does not require users to log in with a password, you can remove your password.

To remove a password

1. Tap User Settings in the main toolbar.
2. Tap Change Password in the dropdown menu.
3. In the Change Password dialog, enter your current password.
4. Leave the New Password and Confirm Password fields blank and tap OK.

Linking to Your Bio-Rad BR.io Account

You must have a password on the ChemiDoc Pro System in order to connect to your BR.io account. See [Creating a Password on page 48](#) for more information. You must also set up a BR.io account. For information about setting up a BR.io account, see the help information in <https://www.br.io/>.

You can connect multiple ChemiDoc Pro System imagers to your BR.io account. When connected, BR.io's Advanced Image Analysis automatically analyzes the image after the imager exports it to BR.io. Advanced Image Analysis includes

- **Automated image analysis** — Automated detection of lanes and bands and, when a standard is applied, calculation of molecular weights for supported single-channel (.scn) and multi-channel (.mscn) files.
- **Comprehensive image data** — Image metadata, acquisition information, and analysis results for each exported image.
- **Structured analysis tables** — Lane and band data, key measurements, and results in an organized table format.
- **Visual overlays** — Overlays such as saturated pixels, borders, lanes, and bands directly on the image for enhanced interpretation.
- **Histogram & Adjustments** — Contrast and brightness controls, including a combination of Low and High values, Gamma (grayscale curve adjustments), Auto adjustment, and image inversion to improve visibility of bands and lanes. These adjustments affect display only and do not modify image data.
- **Standard definition and configuration** — Tools to define standards to calibrate and interpret image data accurately.
- **Background subtraction** — Controls to apply and adjust background subtraction to improve analysis accuracy and clarity.

Before you can connect the ChemiDoc Pro System imager to your BR.io account, the ChemiDoc Pro System Admin must establish a connection to the Internet either through Ethernet or a wireless network communication. For more information, see [Configuring the Network Connection on page 200](#).

Important: If you are linked to BR.io and your Admin has reset your password, you will automatically be unlinked from BR.io. You must relink to your BR.io account.

Tip: For more information about Bio-Rad's BR.io, go to BR.io. From the Home page, you can


- Create a BR.io account
- Explore the BR.io app via video

- Access helpful BR.io guides

Connecting the ChemiDoc Pro System Imager to Your BR.io Account


To connect the ChemiDoc Pro System Imager to your BR.io account

1. Tap User Settings in the main toolbar.




2. Tap BR.io Account.

The system displays a message indicating the account is not linked.



3. Tap Link to link the account.

The ChemiDoc Pro System displays a message while it retrieves an authentication code. When retrieved, the Link to BR.io dialog appears.



Note: The authentication code is valid for one hour after it is retrieved. If you have not linked your instrument within that time frame, you will need to start again.

4. Follow the on-screen procedure:
 - a. Open a web browser and navigate to
br.io/link
 - b. At the prompt, type the code that appears on the Link to BR.io screen and click Submit.
 - c. Follow the prompts on the upcoming screens to complete the linking process to BR.io.
5. When the ChemiDoc Pro System successfully links to BR.io, the BR.io icon appears enabled on the menu bar:



In BR.io, the Instrument Manager displays the connected instrument.

Note: When you log into the ChemiDoc Pro System after establishing the BR.io account connection, you are automatically connected to your BR.io account. When you log in to your BR.io account, your imager appears in the instrument list.


Unlinking the ChemiDoc Pro System Imager from Your BR.io Account

If you need to remove a ChemiDoc Pro System imager from your BR.io account, you must unlink your ChemiDoc Pro System's user account on that instrument from BR.io.

Note: You can link multiple ChemiDoc Pro System imagers to your BR.io account. Unlinking removes only the current imager from your account. All other imagers remain linked to your BR.io account.

To unlink the ChemiDoc Pro System from your BR.io account

1. Tap User Profile.
2. Tap BR.io Account.




3. Tap Unlink.

A status dialog appears to confirm your ChemiDoc Pro System user account is unlinked from BR.io.

Troubleshooting BR.io Connection

If your instrument cannot link to or unlink from BR.io, you'll see the message that follows:



To troubleshoot connection problems

1. Confirm that your ChemiDoc Pro System system has internet connection.
2. Confirm that you have a BR.io account.
3. Confirm that you can access your BR.io account by logging in to BR.io.
4. Restart your instrument and try connecting to BR.io again.

If the problem persists, contact Bio-Rad Technical Support.

Creating the First Administrator Account

This section explains how to create the first administrator account during initial login. For more information, see [Becoming an Administrator after Initial Login on page 57](#)

The first user to log into Image Lab Touch Software can choose whether or not to be an administrator. If not, the user can continue with a standard account.

Image Lab Touch Software provides a Make Me Admin option in the user dropdown menu. The first user to select this option becomes the administrator and sets the administrative password and administrator options.

Until an administrator is appointed

- Any user can become an administrator at any time
- All users can perform administrative tasks
- Users are not required to have passwords

After an administrator has been appointed, only the administrator can create other administrators, and other users' privileges revert to those of a standard user.

Bio-Rad strongly recommends that more than one person is assigned the Administrator role.

Tip: Store your administrative password somewhere safe. For security purposes, administrative password recovery requires the instrument to be serviced.

To create the first administrator account during initial login

1. Tap anywhere in the Welcome screen.
2. Using the on-screen keyboard that appears, tap in a user name and then tap Create. The system prompts you to choose whether you want to be an administrator and displays information that helps you decide.

Note: Names cannot contain the characters \ / : * ? " < . | or start or end with a space.


3. To become an administrator, tap Yes and type a password in the text box that appears. The Administrator Options dialog appears, in which you can choose options for managing Image Lab Touch Software user accounts. For information, see [Setting Administrator Options on page 57](#).
4. Choose the options you want and tap Close. The imager opens to the default view.

Becoming an Administrator after Initial Login

To become an administrator after initial login

Note: This feature is available only if no other user has chosen to be administrator. If an administrator is already appointed, only that user can give that role to other users.

1. In any view, tap Make Me Admin in the User menu.



The Administrator Options dialog appears, in which you can choose options for managing Image Lab Touch Software user accounts. For information, see [Setting Administrator Options on page 57](#)

2. Choose the options you want and tap Close.

Setting Administrator Options

Assigning the Admin role to a user enables the security, file access, and auto-export control features on the imaging system. The Admin Options screen displays two tabs. The Users tab displays the options the

Admin can set for users of the imager; the Export tab displays the options the Admin can set for exporting images.

[Table 7](#) on this page and [Table 8 on page 59](#) list the User and Export options you can set when you log in as an administrator.

Table 7. Users Tab Options.

Option	All User or Individual User Accounts	When Selected
Require Password	All Users	Requires all users to log in with a password. If the user has no password, they must create one.
Enable Password Expiration	All Users	Sets an expiration for all user passwords after six months. Selecting this checkbox also selects the Require Password checkbox.
Enable Login Failure Lockout	All Users	Enables a feature that locks a user out for five minutes after three failed login attempts.
Require Approval for New Users	All Users	Requires administrator to approve all new user accounts.
Require Secure File Export	All Users	When selected, the Require Password, Require Approval for New Users, and Restrict Deletion of Images check boxes are also automatically selected to ensure secure file exports supporting regulatory standards.
Restrict Deletion of Images	All Users	Prevents all users who are not administrators from deleting images.
Admin	Individual User Accounts	Makes this user an administrator.

Option	All User or Individual User Accounts	When Selected
Disabled	Individual User Accounts	Allows the administrator to disable a user's account. Only administrators can access disabled accounts. Note: If the user has linked the ChemiDoc Pro System imager to their BR.io account, the imager is removed from that account when the administrator disables the user. However, their BR.io account remains active and any other linked imager remains linked.
Linked to BR.io	Individual User Accounts	Indicates those users linked to BR.io.
Must Change Password	Individual User Accounts	Requires this user to change their password.
Reset Password	Individual User Accounts	Allows the administrator to create a new password for a user.

Table 8. Export Tab Options (All User Accounts).

Option	When Selected
Restrict Link to BR.io	Restricts users from linking the instrument to BR.io app.
Auto Export to Network Location	Enables the auto-export option and enables the admin to set a specific network location to which all images will be sent. Selecting this option also enables the administrator to create a file naming structure that exports and organizes images in folders by username, instrument, and date.
Restrict Network Export Location	Restricts users to a top-level network location into which they might export files.
Restrict Export to USB	When selected, only administrators can export files to a USB flash drive.
Enable Diagnostic Port	Enables Bio-Rad Technical Support to connect remotely to the imager for diagnosing and troubleshooting issues.

Setting User Options

To set options for users

1. Tap User Settings and then tap Admin Options.

The Administrator Options dialog appears displaying the options on the Users tab by default.

	Admin	Disabled	Linked to PR-Lo	Must Change Password	Reset Password
brio	☒	☐	☐	☐	Reset
CDProUser	☐	☐	☐	☐	Reset
ChemiDoc Pro Admin	☒	☐	☐	☐	Reset

2. In the upper portion of the dialog, select the checkbox for each option you want to enforce.

Note: Selecting Require Secure File Export automatically selects the remaining checkboxes:

- Require Password
- Require Approval for New Users
- Restrict Deletion of Images

3. Clear the checkbox for each option you want to allow.
4. In the lower portion of the grid, select or clear each option that you want to enforce.

Note the following:

- Selecting the Disabled checkbox disables the account but does not delete it. Images taken by the user remain on the imager.

- You cannot clear the Admin checkbox for the logged in Admin user. Only another user with Admin privileges can clear the checkbox of other admins.
- Selecting Reset Password for a user linked to BR.io will automatically unlink the user from their BR.io account.

Important: You must inform the user to relink to their BR.io after creating a new Image Lab Touch Software password.

Note: Leaving the password field blank, and then tapping OK unlinks a user from BR.io.

- You cannot select or clear the Linked to BR.io checkbox. To restrict all users from accessing BR.io, see [Standby Mode on page 42](#)

5. Tap Close to save the settings and close the dialog.

Setting Export Options

To set export options

1. Tap User Settings and then tap Admin Options.
2. In the Administrator Options dialog, tap Export.

The Export Options appear.

The screenshot shows the 'Export' dialog box. It has a title bar with 'Users' and 'Export' tabs. The 'Export' tab is selected. Inside, there are five checkboxes: 'Restrict Link to BR.io', 'Restrict Export to USB', 'Auto Export to Network Location', 'Enable Diagnostic Port', and 'Restrict Network Export Location'. Below these is a text input field with a 'Browse...' button. At the bottom right is a 'Close' button. A section titled 'Export Path Pattern' contains a 'Path Elements' list with 'Date' and 'Instrument' buttons, and a 'Path' area showing 'User Name' followed by two dashed boxes for additional path elements.

3. In the upper portion of the dialog, select the checkbox for each option you want to enforce.

Note the following:

- Selecting Restrict Access to BR.io unlinks the ChemiDoc Pro System imager from all active BR.io accounts and removes the imager from BR.io. Any user who had previously chosen to auto export to BR.io will no longer be able to do so.

For more information, see [Restricting Access to BR.io on page 67](#).

- Selecting Auto Export to Network Location displays the Select Network Location dialog in which you can enter a specific network location to which all images from all users will automatically be sent.

When enabled, the Admin can also create an export path structure in the selected network location in which the exported images will be saved. The path must include the user name and can also include the date and instrument from which the image was exported. For more information, see [Creating an Export Path Pattern on page 63](#).

- Selecting Restrict Network Export Location displays the Select Network Folder dialog in which you:
 - ☐ Enter the file path and tap Connect.
 - ☐ Enter your network user name and password.
 - ☐ Tap OK.
 - Restrict Network Export Location and Auto Export to Network Location are mutually exclusive options. Selecting one checkbox automatically clears the other.
4. Clear the checkbox for each option you want to allow.
 5. Tap Close to save the settings and exit the dialog.

Creating an Export Path Pattern

Selecting the Auto Export to Network Location enables the Admin to select a specific folder on the network into which all auto exported images will be saved.

The Admin can also create a folder structure within the selected network folder into which all images exported by each user will be saved. The path can be any arrangement of user name, date, and instrument.

The export path pattern requires the user name element in the path to prevent overlap of scan image names. The date and instrument elements are optional. With multiple instruments exporting to the same network location, Bio-Rad recommends you include the Instrument element in the path.

You can change the path pattern at any time.

To create an export path pattern

1. Tap Admin Options... from the User Settings dropdown menu.
2. On the Export tab, tap Auto Export to Network Location.

The Export Path Pattern dialog appears in the lower portion of the screen. The User Name element is required by default.

Users

Export

✕

☐ Restrict Link to BR.io
 ☒ Restrict Export to USB

☒ Auto Export to Network Location
 ☒ Enable Diagnostic Port

☐ Restrict Network Export Location

Export Path Pattern

Path Elements

Date

Instrument

Drag and drop elements into the name blocks to create an export path pattern. User Name is required.

Path

User Name

 \

Instrument

 \

Date

 \

3. Do one or both of the following:
 - To add an element to the export pattern, drag an element from the Export Path Elements list into the Path list.
 - To remove an element from the export pattern, drag an element from the Path list to the Export Path Elements list.
4. Repeat [Step 3](#) as applicable.
5. Tap OK to save the format.

The software saves all the images that users acquire using the new path pattern.

To change the export path pattern

To change the export path pattern, do one of the following:

- If you have two or fewer elements in the pattern, drag and drop the elements into the new location and tap OK to save the new format.
- If you have three elements in the pattern, return either the Date or Instrument element to the Path Elements column and move the other elements into the new location. Then drag and drop the remaining element to its location and tap OK to save the new format.

Note: Since the User Name element is required, it will always appear in this path. You cannot remove this element or return it to the Path Elements column. However, you can move it to any available position within the path at any time.

Enabling the Diagnostic Port on the ChemiDoc Pro Imaging System

Important: Cybersecurity is the protection of assets in cyberspace from cyberattacks. Cybersecurity is Bio-Rad's ability to secure its people, information, systems, and reputation in cyberspace. Cyberspace is the always-on, technologically interconnected world; it consists of people, organizations, information, and technology.

Fast reaction is important with cybersecurity issues! If you suspect that there may be a cybersecurity issue concerning your instrument or that cybersecurity has been breached at your site, contact your Bio-Rad representative for technical support immediately.


To reduce cybersecurity threats, all TCP/IP ports on the ChemiDoc Pro System imager are closed by default. To enable Bio-Rad Technical Support team to connect remotely for diagnosing and troubleshooting issues, the ChemiDoc Pro System Administrator can temporarily open a diagnostic port on the instrument.

Note: Rebooting the instrument does not change the state of the port.

Important: Bio-Rad strongly recommends that you close the open diagnostic port after Bio-Rad Technical Support completes troubleshooting the instrument to reduce any threat of cybersecurity attacks.

To enable access to the diagnostic port


1. Log in as an Administrator.
2. In the tool bar, tap the user name to display the account options.
3. Tap Admin Options...



4. Tap the Export tab.
5. Select the Enable Diagnostic Port check box and then tap Close.

To disable the diagnostic port

1. Log in as an Administrator.
2. In the tool bar, tap the user name to display the account options.
3. Tap Admin Options...



4. Tap the Export tab.
5. Clear the Enable Diagnostic Port check box and then tap Close.

Restricting Access to BR.io

Users who have a BR.io account can connect multiple ChemiDoc Pro System imagers to their BR.io account. When connected, users can send images to the BR.io app view images and analysis results within the app or download the images to a connected computer and view them in Image Lab Desktop Software.

The ability to link ChemiDoc Pro System imagers to BR.io is enabled by default. Administrators can restrict users from linking to their BR.io account. When restricted, the BR.io icon no longer appears on the menu bar and the BR.io Account menu item no longer appears in User Settings.


Important: When the option is selected, the ChemiDoc Pro System imager will be unlinked from all active BR.io accounts and removed from BR.io. This cannot be undone. Ensure that all active BR.io

users understand this and are prepared to lose access to BR.io from the imager. Images currently saved in BR.io will remain and users can still access them.


Restrict Linking to BR.io

To restrict linking to BR.io

1. Log in to the ChemiDoc Pro System imager as an administrator.
2. In the main toolbar, tap User Settings and select Admin Options.
3. On the Export tab, tap Restrict Link to BR.io.



You see a dialog informing you that continuing unlinks the ChemiDoc Pro System imager from all active BR.io accounts and removes the imager from BR.io.



4. Tap OK.

The BR.io icon no longer appears on the menu toolbar, the BR.io Access menu item no longer appears on User Settings, and the imager is unlinked from all active BR.io accounts.

Chapter 4 Understanding the Views


Image Lab Touch Software guides you through the processes of acquiring and managing images in four views:

- Camera View
- Preview
- Image View
- Gallery

Color Cues in these views signal different states in the system. For information, see [Color Cues on page 77](#)

Main Toolbar Settings

The main toolbar appears at the top of every Image Lab Touch Software view.



Tapping a toolbar object opens a view or a menu.

Table 9. Main toolbar menu.


Object	Explanation
	Camera view — displays a view of the sample in the sample tray. Also displays a preview image of the sample.
	Gallery — displays thumbnails of all images you acquired. You can view, browse, delete, or export images. Double-tapping a thumbnail displays the image full size in Image View.
	Retake — visible when you acquire a multichannel image, enables you to retake one or more channel images immediately after acquisition.

Table 9. Main toolbar menu., continued

Object	Explanation
[Date, time, and instrument name]	Date, Time, and Instrument Name — displays the current date and time, and the name of the instrument if your administrator issued it a name. Your Image Lab Touch Software administrator can change these settings in the System Settings menu.
	BR.io Link Status — displays the status of the ChemiDoc Pro System connection to Bio-Rad's BR.io app: ■ Current logged-in user account is not linked to BR.io
	■ Current logged-in user account is linked to BR.io
	System Settings — menu enabling the user to set the following system options and to calibrate the White Tray: ■ Instrument name ■ Standby idle time ■ Date and time ■ Time zone ■ System language (either English, default, or Chinese) ■ Network configuration ■ Brightness ■ Sound volume Tip: When the instrument identifies the White Tray for the first time, a Calibration dialog automatically appears. Note: If an administrator exists on the ChemiDoc Pro System instrument, only the administrator can access the Instrument Name, Date and Time, Time Zone, Language, and Network Configuration options.
	Help — displays procedures and concepts for the view on screen.
	User Settings — menu that accesses commands to change your password, set a file naming format for acquired images, view Admin settings, lock the display, or log out. Name of current user appears to its right.

Camera View

When you log in to the imaging system, Camera view displays the imaging stage as the default view. An orange button with an exclamation point on the bottom left corner indicates that you must take an action before acquiring an image. Tap the button to find more information.



When you place a sample in the imaging system, Camera view displays the sample as it appears in the current tray. From the left pane, you can choose imaging settings such as image size, application, and exposure, for each channel you want to acquire.

After you choose settings that are compatible with the inserted tray, the orange button changes to a green button with a camera and you can acquire the image.

The acquired image appears full size in Image View and also as a thumbnail in the Gallery.


- **Main toolbar** — displays access to Camera view or the Gallery, status of BR.io connectivity, and access to system settings, help topics, and user settings. For more information, see [Main Toolbar Settings on page 69](#).
- **Imaging area** — displays the sample in the imaging system.

- **Image Settings tiles** — tapping Application or Exposure in a tile displays
 - ☐ Single/Multi — select either single-channel and multichannel imaging modes.
 - ☐ Image Size — select small, medium or large predefined image areas as well as the option to manually define an image area size.
 - ☐ Application — select an application for the stain used and tray inserted in the imager.
 - ☐ Exposure — set image exposure time to be set automatically or manually.
 - ☐ Preview — quickly displays an image that you can use to optimize acquisition on a specific sample region when using automatic exposure.
- **Image Settings tiles** — tapping Application or Exposure in a tile displays options for that setting.
- **Camera button** — tapping this button at the bottom left of the screen acquires an image of the sample.

For more information, see [Acquiring an Image — General Steps on page 90](#).

Preview


Preview quickly displays an image of the sample in the imager so you can determine whether sufficient sample is visible and identify the region for which you want to set an automatic exposure.



For more information, see [Previewing an Image on page 104](#).

Image View

When you acquire an image, it is automatically saved to the Gallery and opened in Image View. The image automatically opens in full-size view.



The Image View Toolbar

The Image View toolbar appears at the bottom of Image View. Its options enable you to fine tune and manage images.





Table 10. Image View Icons.

Icon	Description
	Visible when a single image is displayed. Tap to scroll through Previous and Next images selected for display as they appear in the Gallery.
	Copy Zoom — visible when multiple images are displayed. Selecting a zoomed image and then tapping this icon copies the zoom setting of the selected image to the other displayed images.
	Transform — enables you to optimize image appearance by adjusting brightness and contrast.
	Image Info — lists acquisition details for the active image and the name of the user who acquired it. You can rename an image or add notes about it.
	Merge — combines up to four images into a multichannel image.
	Print — prints the displayed image to the local printer.
	Delete — deletes the displayed image.
	Send/Save — saves the displayed image to a network drive, USB drive or BR.io.

The Gallery

The Gallery displays thumbnail images of all acquired images, ordered and grouped by date acquired. The most recent acquisition date appears first. The default name is <user name> <date and time of acquisition>. You can change this name in the Image Info box.




Tap a thumbnail image in the Gallery and then tap the orange View button to

- Open the selected image in full size in Image View
- Delete selected images
- Save selected images to a network drive, an attached USB drive, or BR.io

Tap the zoom icons to increase or decrease the size of the thumbnails.

To compare images, you can select up to four images in the Gallery to display in Image View.



Note: If you are viewing multiple images or a multi-channel image, tap the icon in the upper right corner of any single image to switch to Single View at full size.


For more information, see [Comparing Images on page 140](#).

Color Cues


Image Lab Touch Software color cues indicate the various states of the system.

Note: In this section, the color cue definition is followed by an example screen, in which a red outline highlights the use of the color cue.


Blue indicates a selected object. In this image, Camera view and single image are selected.



In the Gallery and in Image View, selected images are outlined in blue.



Green and **Orange** indicate active objects. In the following graphic, the green color cue indicates that you can select Gallery. The orange color cue indicates that you can create a multichannel image.



The image capture button on the bottom left corner appears in one of three colors:

- Green
- Orange
- Red


Green indicates that the camera is ready; you can capture an image of the sample.



Orange indicates that an action is required before you can continue. In the next image, the orange exclamation point appears in place of Camera to indicate that an error message requires action.




- Tap the orange exclamation point to display a message that explains what to do.



Red indicates a critical error.



- Tap the red exclamation point to display the message. You must log out of Image Lab Touch Software and restart the imager to correct the error.



Chapter 5 Choosing a Sample Tray

Before you acquire an image, you must select a sample tray that is designed for the application.

The imaging system supports the following trays:

Icon	Sample Tray Name
	UV/Stain-Free Tray
	White Tray
	Blue Tray
	Blot Tray

The imaging system automatically detects the type of sample tray inserted into the ChemiDoc Pro System imager. If the tray in the transilluminator drawer does not support the application, an error message appears and the imaging system does not acquire the image.


The UV/Stain-Free Tray is a universal tray for the ChemiDoc Pro, ChemiDoc Go, and GelDoc Go Imaging Systems. The Blue and White Trays are interchangeable between the ChemiDoc Pro and ChemiDoc Go imagers, but not GelDoc™ Go. ChemiDoc Pro System trays are identified by a blue or white triangle (▲) on the label, depending on the tray type. Ensure that you insert the blue or White Tray that is appropriate for your imager.

Some fluorescent reagents have excitation peaks in both UV and blue wavelengths. In this case, either excitation source can be used. However, the resulting images are not identical. Using the recommended tray with these fluorescent reagents provides a better signal-to-noise ratio, which increases sensitivity.

When two tray types can be used, both are shown. An asterisk identifies the recommended tray.



Caution: The materials in the sample trays and transilluminator drawer have limited acidic and basic chemical resistance, which includes many Coomassie-based stains and chemiluminescent reagents. Thoroughly wipe down surfaces with deionized water and laboratory tissues if exposure to acidic or basic solutions occurs.



Applications Listed by Tray Type

The ChemiDoc Pro System ships with the UV/Stain-Free Tray, Blot Tray, Blue Tray, and White Tray. Applications you can use with each tray are listed in the following tables.

UV/Stain-Free Tray

Table 11 lists the applications for the UV/Stain-Free Tray.

Table 11. Applications for UV/Stain-Free Tray.

Application	
■ Diamond Stain	■ Oriole Gel Stain
■ Ethidium bromide (EtBr)	■ ProQ Emerald 300
■ Flamingo Stain	■ Stain-Free gels and blots
■ GelGreen Stain	■ SYBR [®] Stains
■ GelRed Stain	■ SYPRO Ruby Stain
■ GelStar Stain	■ UView Stain

Blue Tray

Table 12. Applications for the Blue Tray.

Application	
■ Coomassie Fluor Orange	■ GelStar Stain
■ Diamond Stain	■ ProQ Emerald 488
■ Flamingo with XcitaBlue	■ SYBR [®] Gold Stain
■ Fluorescein	■ SYBR [®] Green Stain
■ GelGreen Stain	■ SYBR [®] Safe Stain

White Tray

Note: The White Tray must be calibrated before it is used for the first time.

Table 13. Applications for the White Tray.

Application	
■ Coomassie Blue	■ Silver Stain
■ Epi-White	■ Fast Blast

Calibrating the White Tray

The optional White Tray requires calibration before it can be used for the first time.


Note: If you subsequently obtain another White Tray, Bio-Rad recommends that you calibrate the new tray.

When the imaging system detects that a White Tray has been inserted for the first time, a message indicates that the tray is not calibrated and lists steps to calibrate it.

To calibrate the White Tray

1. Complete the steps listed in the message box that appears.
2. Tap Calibrate.

The system starts calibrating the White Tray. A progress bar monitors the process.



A message notifies you when calibration is complete.


3. Tap OK to close the message.

Calibrating a Replacement White Tray

When you replace the White Tray, Bio-Rad recommends that you calibrate the new tray.

To calibrate a replacement White Tray

1. Tap User Settings, and then tap Calibrate White Tray...



A message displays the steps to calibrate the tray.

2. Complete the steps listed in the message box.
3. Tap Calibrate.

The system starts calibrating the White Tray. A progress bar monitors the process.

A message notifies you when calibration is complete.

4. Tap OK to close the message.

Blot Tray

Table 14 lists the applications for the Blot Tray.

The table below lists the applications for the Blot Tray.

Table 14. Applications for a Blot Tray.

Application	
■ Alexa 488	■ DyLight 650
■ Alexa 546	■ DyLight 680
■ Alexa 647	■ DyLight 800
■ Alexa 680	■ Fluorescein
■ Alexa 790	■ IRDye 680RD
■ Amido Black	■ IRDye 800CW
■ Chemiluminescence	■ Krypton
■ Colorimetric	■ Ponceau S
■ Coomassie Blue*	■ Pro-Q Diamond
■ Copper Stain	■ Pro-Q Emerald 488
■ Cy2	■ Rhodamine
■ Cy3	■ Stain-Free Blot
■ Cy5	■ StarBright B520
■ Cy5.5	■ StarBright B700
■ Cy7	■ SYPRO Ruby Blot
■ DyLight 488	■ Zinc Stain
■ DyLight 550	

Chapter 6 Acquiring Images

Instructions for acquiring an image apply to both single-channel and multichannel images unless they are preceded by (Single Channel) or (Multichannel).

The steps for acquiring singlechannel and multichannel images are similar. Acquiring a multichannel image requires repeating some steps for additional channels, and a few procedures are specific to single or multichannel images.

Before you can acquire an image, you must place a sample on the sample tray and then place the tray on the imaging stage. You can specify acquisition settings before you place the sample on the sample tray or after you place the tray in the transilluminator drawer. The imager retains your settings until you change them.

Placing the Sample in the Imager

You must use the tray that supports the application you select. The imaging system detects the type of sample tray on the imaging stage. If the tray in the transilluminator drawer does not support the selected application, an error message appears and you will not be able to acquire the image.

To place the sample in the imager

1. Place the sample face up on the sample tray.

Tip: If you plan to zoom in or out on the image, center the sample on the tray as accurately as possible. Use alignment templates provided with instrument accessories and/or the dashes located on the sample trays to center samples.

2. Pull out the transilluminator drawer.
3. Place the sample tray on the imaging stage.
4. Close the transilluminator drawer.


Acquiring an Image — General Steps

These general steps outline the workflow for acquiring an image.


Note: You can configure up to four channels on the ChemiDoc Pro System for multichannel acquisition. The image size you choose applies to all channels in the acquisition.

To acquire an image

1. In Camera view, do one of the following:
 - (Single Channel) Tap Single to configure a single-channel image.



- (Multichannel) Tap Multi to configure a multichannel image.



2. Specify the image size so that the sample fills as much of the screen as possible.

3. (Multichannel) Select a channel color or keep the default color. (You can change the channel color at any time.)
4. Choose the application.

Note: ChemiDoc Pro System also enables you to select custom applications in a multichannel image.

5. Preview the image (optional).
6. Keep the default automatic exposure option or change the exposure options.

Note: When you set an automatic exposure time and specify a region of interest, the optimal auto-exposure time applies to that region only.

7. (Multichannel) Repeat steps 3–7 for the remaining channels.
8. Tap Camera to acquire the image.

During acquisition, a progress bar appears on the screen, and the power LED blinks green. When acquisition completes, the image appears in Image View. In Image View you can

- Adjust the appearance of the image
- Rename the image
- Delete the image

For more information, see [Chapter 10, Managing Images on page 153](#)

Tip: (Multichannel) If you cancel the process during multichannel acquisition, Image Lab Touch Software stops acquiring images and stores the images that were acquired in the Gallery.

Setting Image Type and Size

Image type and size settings appear at the top of the left pane in Camera view. In multichannel acquisitions, the image type and size you choose apply to all channels.

Choosing Image Type

To choose an image type

- ▶ Tap Single or Multi to acquire a single-channel or multichannel image.



Choosing Image Size

You can choose a preset image size or specify a custom size. The preset sizes correspond to these Bio-Rad gels:


- **Small** — Mini-PROTEAN
- **Medium** — Criterion
- **Large** — Pulsed Field Agarose

To choose a preset image size

- ▶ Tap Image Size to select a size in the dialog that appears.



The dimensions of the selected image size appear under Image Size.



To specify a custom image size for a gel or blot image

1. In Camera view, tap Image Size.
2. Tap the W (width) or L (length) box. When you enter one dimension, the software automatically calculates the other according to the image system's 3:2 aspect ratio.
3. Using the keypad, enter the width or length of the image (in cm).

Valid width values are 9.0–21.0 cm. Valid length values are 6.0–14.0 cm.

To change the image size manually

- ▶ Place a thumb and one or two fingers slightly apart on the screen and move them together (pinch to zoom) without lifting them from screen until the image is the size you want.


Choosing the Application

You can choose from a list of predefined applications for common sample types. You can also create a custom application.

Image Lab Touch Software supports four application categories: nucleic acid gels, protein gels, blots, and custom applications. Multichannel images can be acquired only for blots and custom applications.

Important: You must use the tray that supports the application you select. The imager detects the type of sample tray on the imaging stage. If the tray in the transilluminator drawer does not support the selected application, an error message appears when you try to acquire the image.

When you choose an application, the software selects the appropriate filter and illumination source. Detailed settings appear in the imaging settings tile under the name of the selected application. The default automatic exposure setting also appears. You can change the default exposure setting.




When you select a chemiluminescent application, the optimal binning level also appears under Exposure.

To choose an application

1. In Camera view, tap Application in an imaging settings tile.


The Application box appears.



2. Under Choose Application Category, tap an application category.

The Choose Application list displays only applications compatible with the category you selected.

For example, when you tap Blots, only applications for blots appear.



3. Tap an application.

(Multichannel) When you configure the first channel, the system eliminates applications that are redundant or incompatible with the application you selected, and so on for the second, third, and fourth channels you configure.

4. (Multichannel) Repeat steps 1–3 for each channel you want to add.


Renaming an Application

Administrators can rename an application.

To rename an application

1. In Camera view, tap Application in an imaging settings tile.

The Application box appears.



2. Under Choose Application Category, tap an application category.
 3. Tap an application.
 4. Tap the pencil icon ().
 5. In the Application Name dialog, tap in the application name field to display the keyboard.
- Note:** Application names cannot contain the characters \ : * ? " < > | or start or end with a space.
6. Enter the new application name.
 7. Tap OK to save.

To reset the application name to its predefined value, follow the same steps but tap Reset instead of OK, and then tap OK.

Single or Multichannel Images

Note: Only applications for blots are available for multichannel images.


You can configure 1–4 channels on the ChemiDoc Pro System imaging system for multichannel acquisition. The image size you choose applies to all channels in the acquisition.

Important: You must select an application for each channel before adding another channel.

Note: If enabled, you can also include custom applications in a multichannel image.

Important: Selecting a custom application from a single-channel protocol for a multichannel protocol removes it from the single-channel protocol.

When you choose an application for a channel, a plus sign surrounded by a dotted outline tile appears below the selected channel. Tapping inside the outline box changes it into an imaging settings tile for the next channel.



(Multichannel) Selecting a Channel Color


Assigning channels different colors makes it easier to identify the channels in a composite image. You can use any channel color with any application when you specify channel settings.

Note: There is no relationship between the emission wavelength of the sample and the channel color.


Acquisition options for a channel display a default channel color. You can keep the default color or change it. You can change a channel color at any time. If you change the channel color to one already assigned to another channel, the channels swap colors.

To select a channel color

1. Tap to view the color list.



2. Tap a color to select it.



Note: The gray channel is only available if there are four channels.

Creating Custom Applications

Admin users can enable other users to create, modify, and delete custom applications. Custom applications enable users to assign specific settings for sample imaging based on the light/excitation source, emission filter, and tray. You can create single-channel or multichannel custom applications.


To enable this feature, Admins must deselect the Restrict Custom Applications checkbox in Admin Options. For more information, see [Setting Administrator Options on page 57](#).

Note: You cannot create more than 17 custom applications.


To create a custom application

1. In Camera view, tap Application in an imaging settings tile.

The Application box appears.




2. Tap Custom.



3. In the Choose Application Category dialog, tap the plus icon () to create a new custom application.

The Custom Application dialog appears.



4. In the Custom Application dialog, do the following:
 - a. Tap the Application Name text box and enter a unique name for the application.
Note: Names cannot contain the characters \ / : * ? " < . | or start or end with a space.
 - b. Tap anywhere outside of the keyboard to save the application name.
 - c. (Optional) Set the iris percentage (10%, 25%, 50%, or 100%) to control how much light enters the lens.
Note: Lower percentages reduce brightness and increase depth of field, while higher percentages allow more light for brighter images.
 - d. (Optional) In the Focus Offset field, enter the offset (from 0 to 4 centimeters) to adjust the focal plane above the platen and accommodate sample thickness. For more information about Focus Offset, see [Adjusting the Focus Offset on page 103](#).
 - e. Select the tray type.
 - f. (Optional) Define the light direction.
Note: The wavelength will change based on the selections.

- g. Define the excitation source.
 - h. Select the desired emission filter.
5. Tap Save to confirm the new custom application.

After creating an application, only the user that created it has access.


Editing Custom Applications

You can edit an existing custom application to change the tray type, emission filter, excitation source, the iris percentage, focus offset, or name.


To edit a custom application

1. In Camera view, tap Application in an imaging settings tile.


The Application box appears.



2. Tap Custom



3. In the Choose Application Category dialog, tap the custom application, and then tap the pencil icon ().
4. In the Custom Application screen, make your edits.




5. Enter the application name, and then tap Save.

Deleting Custom Applications


You can delete an existing custom application.

To delete a custom application

1. In Camera view, tap Application in an imaging settings tile.
The Application box appears.



2. Tap Custom



3. In the Choose Application Category dialog, tap the custom application, and then tap the pencil icon ().

4. Tap Delete.

Important: After deleting a custom application, you cannot recover it.

5. Tap OK.

Adjusting the Focus Offset

The Focus Offset setting in a custom application allows you to shift the focal plane above the platen to accommodate sample thicknesses from 0 to 4 centimeters. This includes items such as petri dishes, microtiter plates, and multiwell plates.


Increasing the focus offset increases the minimum image size.

Note: The pixel size shown in the image information of the acquired image displays the selected image size and does not account for the offset.

Important: When acquiring an image, Bio-Rad recommends that users apply the same focus offset to every channel in a multichannel custom application. This ensures all images are captured on the same focal plane, allowing features to align properly and enabling accurate intensity measurements for quantitative analysis.

Previewing an Image

When you put a sample in the imager and close the drawer, Preview appears at the bottom of the imaging settings tile.




When you tap Preview for an auto exposure, the system displays an image of the sample using the appropriate light source for the application.

View the image to identify a region of interest by resizing or moving the rectangle. If sufficient sample is visible, you can then select either Auto Optimal or Auto Rapid exposure for the image you want to acquire.

Important: Keep the transilluminator drawer closed while viewing the preview image.

To preview an image

1. Specify an application.
2. Tap Preview to view an image of the sample.
3. Inspect the preview image to verify that important sample features are visible in the sample.



4. Use the grip on each corner to adjust the preview window and specify a region of interest (for example a lane or band).



For information, see [Specifying the Region of Interest for Auto-Exposure on page 111](#).

5. Tap Camera to start the image acquisition.

To clear the preview image, do any of the following:

- Open the drawer.
- Select an application that uses a different tray.
- Switch between single and multichannel modes.
- Log out.
- Delete a channel and then add it again.

Exposure Settings

Steps for specifying exposure settings are specific to the type of application you select, and how you choose to expose it: automatically (Optimal, Rapid, or Auto SAM for blot applications) or manually. Refer

to the subsection about the type of application you want to image.

- General gels and blots
- Stain-Free gels
- Chemiluminescent blots

Note: Chemiluminescent Blot is the only chemiluminescent application available for the ChemiDoc Pro Imaging System. The system does not support other no-light applications.

Setting Exposure for General Gels and Blots

To choose an automatic exposure setting for a general gel or blot

1. In Camera view, tap Exposure.
2. Tap Auto, and then tap Optimal Auto-exposure or Rapid Auto-exposure. For information, see [Automatic Exposure Settings on page 109](#).
3. (Optional) Tap Preview, and then specify the region of interest in the preview image.
4. Tap Camera to acquire the image.

To manually set an exposure time for a general gel or blot

1. In Camera view, tap Exposure.
2. Tap Manual.
3. Tap Set Manual Exposure Time.
4. Enter the time in the text box using the numeric keypad.
5. Tap Camera to acquire the image.

Setting Exposure for Stain-Free Gels

Before you set the exposure time for a Stain-Free gel, you can select a gel activation setting.

To select a gel activation setting

1. Tap Exposure.
2. Under Select Gel Activation, choose one of the following:
 - **None** — to reimage a previously activated Stain-Free gel or for no activation.
 - **Blot** — to activate your Stain-Free gel for subsequent use in western blotting.
 - **Gel** — to activate your Stain-Free gel for maximum signal intensity. Choose *Gel* if your Stain-Free gel will NOT be used in Western blotting.

To choose automatic exposure settings

1. Tap Auto.
2. Tap one of the following radio buttons:
 - Optimal Auto-exposure
 - Rapid Auto-exposure. For information, see [Automatic Exposure Settings on page 109](#)
 - (Blot mode only) Tap Stain-Free SAM to acquire the Stain-Free image using Optimal Auto-exposure with SAM image acquisition. This mode acquires three cumulative images during the last seven seconds of activation reducing the gel's exposure to UV light. Use Stain-Free SAM mode when binding antibodies to downstream Stain-Free blots.

Note: Additionally, selecting None or Gel activations disables the Stain-Free SAM radio button. For more information about Stain-Free SAM, see [Acquiring Images Using Stain-Free SAM on page 118](#)
3. Tap Camera to acquire the image.

To set a manual exposure time

1. Tap Manual.
2. Tap the sec (seconds) box to display the keypad.
3. Enter the exposure time in seconds.
4. Tap Done.
5. Tap Camera to acquire the image.

Setting Exposure Time for a Chemiluminescent Blot

Note: Chemiluminescent Blot is the only chemiluminescent application available for the ChemiDoc Pro Imaging System. The system does not support other no-light applications.

You can choose automatic or manual exposure settings and adjust the binning level for the Chemiluminescence application.

Image Lab Touch Software estimates the best exposure time for obtaining good-quality images with the optimal dynamic range from the Chemiluminescence application.

Automatic Exposure Settings

You can choose how Image Lab Touch Software calculates an automatic exposure. Three automatic exposure settings, Optimal, Rapid, and Stain-Free SAM are available:

- When you choose Optimal, the dynamic range of the image is maximized to show faint bands. When you specify a region of interest, the dynamic range is optimized for the specified area only.
- When you choose Rapid, the software calculates a reasonable exposure time more quickly than Optimal by allowing a wider window of intensity to capture a reasonable image, but with a greater chance of overexposed or underexposed images.
- (Single Channel blot applications only) When you choose Stain-Free SAM, the software automatically captures and combines short exposures, analyzing signal, background, and noise to optimize band visibility while minimizing UV exposure. For more information, see [Acquiring Images Using Stain-Free SAM on page 118](#).

Tip: Using Rapid Auto-exposure can help you estimate manual exposure time. Choose Rapid Auto-exposure and acquire the image. When the acquired image appears, tap Image Info in the lower toolbar to view the exposure time. Using this exposure time as a baseline, manually set the exposure time to obtain the image quality you want.

Name
ChemiDoc Pro Admin 2025-12-04 14h00m06s

Notes

Acquisition Information

Imager	ChemiDoc Pro
Exposure Time (sec)	0.500 (Manual)
Instrument Name	SIM-CDPro-1
Serial Number	SIM-CDPRO-PM-1
Software Version	0.9.0.12180
Application	CustomApp
Excitation Source	Blue Epi Illumination
Emission Filter	590/110 Filter
Filter Info	[CHEZ Lens Distortion]
Focus Offset (cm)	2.0
Iris	25%
Flat Field	Applied (Blue Epi)

Image Information

Acquisition Date	12/4/2025 1:59:49 PM
User Name	ChemiDoc Pro Admin
Image Area (mm)	X: 210.0 Y: 139.8
Pixel Size (µm)	X: 69.8 Y: 69.7
Data Range (int)	628 - 24352

Setting the Exposure Automatically for Chemiluminescent Blot Applications


You can choose automatic or manual exposure settings and adjust the binning level for a chemiluminescent application. Image Lab Touch Software estimates the best exposure time for obtaining good-quality images with the optimal dynamic range from chemiluminescent applications.

By default, the software selects a binning level based on either the selected application or on a combination of application and image size.

To choose an automatic exposure setting for a chemiluminescent application

1. In Camera view, tap Exposure.
2. Review the recommended binning setting on the scale and tap a different binning setting if needed.

Tip: Bio-Rad recommends starting with the optimal binning setting, examining the result, and then adjusting settings when acquiring subsequent images.



LEGEND

	Binning level
	Selected binning setting
	Optimal binning setting

3. Tap one of the following:
 - Optimal Auto-exposure
 - Rapid Auto-exposure
 - Smart SAM

4. (Optional) Tap Preview to obtain a preview image and then specify the region of interest.
5. Tap Camera to acquire the image.

Specifying the Region of Interest for Auto-Exposure

When you preview an image, you can specify a region of interest such as a band. Image Lab Touch Software sets the automatic exposure so that the brightest pixels in the region of interest are exposed to near saturation, and uses that exposure for the entire image.

Because Image Lab Touch Software images the entire screen view, specifying a region of interest is especially valuable when setting automatic exposure for chemiluminescent or fluorescent samples.

Note: You cannot specify a region of interest for a Stain-Free gel.

Tip: Because protein standards are intense, consider excluding them from the region of interest. If you do not exclude standards, fainter features might not be visible.


Consider specifying the region of interest when you want to do the following:

- To evaluate relative signal intensities, all features that you want to compare must be unsaturated. To prevent saturation of features, specify a region that encompasses the features to be compared.
- To push the limits of sensitivity, specify a region of faint or no apparent signal. The software optimizes the exposure to reveal features in the specified region, but this might cause saturation of more intense features on the blot.

Important: Do not open the drawer during preview. Opening the drawer clears the preview image.

To specify the region of interest in a preview image


1. Tap Preview in the imaging tile and wait for the light source to warm up.




A low-resolution image of the blot appears with a selection rectangle you can adjust to surround an area of interest.



2. To resize the rectangle, drag a corner.
3. To move the rectangle, drag an edge.



4. Tap Live to return to a view of the sample on the imaging stage.



5. Tap Camera to acquire the image.


Setting the Exposure Manually for Chemiluminescent Blot Applications

For a manual exposure time, the following options are available:

- **Set Manual Exposure Time** — to enter time manually in seconds.
- **Configure Signal Accumulation Mode** — (chemiluminescent blots and single-channel only) to have the imager capture a series of images with a range of exposure times.

To choose a manual exposure setting for a chemiluminescent blot

1. In Camera view, tap Exposure.
2. Tap Manual.
3. Review the recommended binning setting on the Image Resolution/Time scale and tap a different binning setting if needed.



LEGEND

	Binning level
	Selected binning setting
	Optimal binning setting

4. Tap Set Manual Exposure Time.
5. Tap the sec (seconds) box to display the keypad.
6. Enter the exposure time in seconds.

Tip: You can use the exposure time from a Rapid Auto-exposure image as a baseline for estimating exposure time.

7. Tap Camera to acquire the image.

(Single Channel) Acquiring Signal Accumulation Mode (SAM) Images

SAM is useful for determining the best exposure time for a chemiluminescent blot sample.

SAM produces a series of cumulative images acquired using the range of exposure times you set. After using SAM to determine the best exposure time, Bio-Rad recommends that you acquire a single image of the sample using the optimal exposure to reduce the amount of noise added by the accumulation process.

During SAM acquisitions, a preview of each image appears so you can monitor its quality.

You can also acquire images using Stain-Free SAM. For more information, see [Acquiring Images Using Stain-Free SAM on page 118](#).

Acquiring SAM Images Manually

To manually calculate the SAM exposure setting


- Estimate the shortest and longest exposure times you think will achieve the optimal image.

For example, if you think the minimum time to acquire an image is 60 seconds and the longest time is 180 seconds, set these as the first and last values and then define the number of images to be acquired during the interval.

Tip: If no features appear in the resulting SAM images, acquire a second group of SAM images using longer exposure times.

To manually acquire SAM images

1. In Camera view, tap Exposure.
2. Tap Manual and then tap Configure Signal Accumulation Mode.
3. Enter the exposure times, in seconds, in the First Image and Last Image boxes.




4. Enter the total number of images in the Images box. The recommended total is 3–5 images.
5. Tap Camera to acquire the image.


The last image acquired appears full size in Image View.

To obtain the exposure time for the preferred SAM image


1. In the Gallery, tap the SAM stack thumbnail.



Individual SAM image thumbnails appear.



2. Tap the image with the exposure you prefer to select it.



3. In the bottom toolbar, tap View Selected Images to display the selected image in Image View. The image you selected appears full size in Image View.
4. In the Image View bottom toolbar, tap Image Info to open the Image Information box.
5. Under Acquisition Information, obtain the Exposure Time (sec) for the selected image.

Acquisition Information	
Imager	ChemiDoc Pro
Exposure Time (sec)	100.000 (Signal Accumulati...
Instrument Name	ChemiDoc Pro Instrument
Serial Number	SIM-CDPRO-MAIN-1
Software Version	0.9.0.11380
Application	Chemiluminescence
Excitation Source	No Illumination
Emission Filter	511/252 Filter
Binning	2x2
Filter Info	[mBioBert kernelSize = 1 f...
Flat Field	Applied (Lens)

6. Close the Image Information box.

To acquire an image using the best SAM exposure time


1. Tap Camera view.
2. Tap Exposure and then tap Manual.
3. Tap Set Manual Exposure Time.
4. Tap the sec (seconds) box to display the keypad.
5. Enter the Exposure Time value you obtained from the Image Information box.
6. Tap Camera to acquire the image.

Expanding and Collapsing SAM Groups

In the Gallery view, you can expand SAM groups so that each SAM image is visible.

To expand the SAM group

Tap the SAM stack thumbnail.



The SAM group boundaries appear as dark gray lines on the left side of the first SAM image and the right side of the last SAM image.

Adjusting SAM Acquisition Settings

You can preview SAM images as they are acquired and cancel the acquisition at any time. You can then adjust the SAM settings and start SAM acquisition with the adjusted settings.

When you cancel a SAM acquisition in progress, the imager stops acquiring images and stores the images already acquired in the Gallery. For example, if you set the total number of images to 10 and cancel while image 4 is being acquired, acquisition stops immediately, and images 1–3 are stored in the Gallery.

To cancel SAM acquisition and adjust acquisition settings

1. Carefully preview each image as it is acquired.
2. If an image is not to your liking, tap Cancel.

The software stops the acquisition, stores acquired images in the Gallery, and displays the last image acquired at full size.

3. Go to Camera view and tap Exposure.
4. Change the SAM settings.
5. Tap Camera to start another SAM acquisition.

Acquiring Images Using Stain-Free SAM


Stain-Free SAM automatically acquires a series of short, cumulative exposures. These images are combined to enhance band visibility, and you can select the optimal image from the set. This workflow is especially useful for ensuring that the best exposure is captured automatically.

Stain-Free SAM improves Stain-Free gel imaging for downstream Western blotting by performing the activation and acquisition steps simultaneously. This mode acquires three cumulative images during the last seven seconds of activation reducing the gel's exposure to UV light. Use Stain-Free SAM for Stain-Free blots when an antibody targets epitopes containing tryptophan.

To acquire images with Stain-Free SAM (Stain-Free gels)

1. In Camera view, tap Application.
2. Tap the Protein Gels application category.
3. Tap Stain-Free Gel.
4. Tap Exposure in the left navigation bar.
5. Tap Auto.
6. Tap the Blot check box.

7. Tap the Stain-Free SAM radio button. This mode acquires three cumulative images during the last seven seconds of activation, reducing the gel's exposure to UV light.



8. Tap Camera to acquire the image.
9. The imager performs the activation and acquires the image.

Stain-Free SAM appears in image information.

Acquiring the Image

After you specify the image settings, you can acquire the image. Make sure the transilluminator drawer is pushed in all the way and closed.


Note: If an exclamation point appears on the screen in place of the Camera, a problem is preventing image acquisition. The color of the exclamation point indicates the severity of the problem. An orange exclamation point indicates that an action must be taken before the image can be acquired. A red exclamation point indicates that the camera is disconnected. Log out of Image Lab Touch Software and restart the imaging system to correct the error. If the problem persists, contact Bio-Rad Technical Support.

To view the error message

- Tap the button in the bottom left corner of the screen.



A message appears explaining how to correct the error.



To acquire a gel or blot image

- Tap Camera.

Acquisition starts. A progress bar monitors the acquisition.

When the image is acquired, it appears in Image View. You can adjust the appearance of the image.

You can also rename or delete the image in this view.

(Multichannel) If you cancel the process during multichannel acquisition, the software stops acquiring images and stores the images that have been acquired in the Gallery.

(Stain-Free Gel) Skipping Gel Activation

When you select a gel activation setting for a Stain-Free gel and tap Camera, gel activation starts before acquisition. A preview of the image appears. You can monitor the progress of gel activation and stop it when the gel is properly activated.

To stop gel activation and skip to acquisition

1. Monitor gel activation carefully.
2. When the gel is properly activated, tap Skip in the progress box.

The software skips the remaining time for gel activation and acquires the image.

(Stain-Free Gel) Acquiring an Image after Canceling Acquisition

Important: Do not open the drawer or move the sample.

When you activate a Stain-Free gel and then cancel the image acquisition in progress, you can use the same gel, keep or change exposure settings, and acquire the image again.

To acquire an image after canceling acquisition

1. Tap Exposure.
2. Select None.

3. Set exposure options.
4. Tap Camera to reacquire the image.

(Multichannel) Retaking an Image

You can retake one or more images in a multichannel image after acquisition. You can also delete one or more channels to generate a different multichannel image. The new multichannel image results from the combination of the remaining channel images.

Important: Do not leave the current view, open the drawer, or log out. Any of these actions removes the Retake option from the main toolbar.


You can change the exposure settings and retake the channel image to achieve different results. You can also change automatic or manual exposure options.

When you retake an image, Image Lab Touch Software does the following:

- Replaces the channel image you specify with a new image acquired using modified exposure settings. The other channel images are retained.
- Generates a new composite image by combining the channel image you retake with the channel images you keep. (A *composite image* combines the data from the channel images into one image.)
- Stores the original multichannel image and the new multichannel image in the Gallery. (A *multichannel image* consists of a composite image plus the channel images generated during one acquisition.)

To retake a channel image

1. Tap Retake in the main toolbar.



2. Change the exposure settings in one or more channels.

The previous and current settings appear under Exposure in the imaging settings tile.

3. (Optional) Select an area of interest.
4. (Optional) To revert to the previous settings, tap Keep in the imaging settings tile.
5. To retake the image, tap Camera.

Chapter 7 Excising Bands from Samples

You can excise bands of interest from agarose or acrylamide gels for applications such as mass spectrometry or DNA cloning.

The procedure for excising bands varies depending on the sample tray in use.



Caution: Before you begin excising bands, ensure that you have on the required protective gear and that the UV shield is installed.

Caution: When excising bands on the UV/Stain-Free Tray, keep the UV shield open for as little time as possible.

Caution: Sharp cutting tools can easily damage the surface of the tray. To avoid this, place a sheet of clear glass or plastic on the tray before you add the gel sample. Use a *chopping* motion rather than a *sawing* motion.

Caution: The materials in the sample trays and transilluminator drawer have limited acidic and basic chemical resistance, which includes many Coomassie-based stains and chemiluminescent reagents. Thoroughly wipe down surfaces with deionized water and laboratory tissues if exposure to acidic or basic solutions occurs

Excising Bands on a UV/Stain-Free Tray



WARNING! Transilluminators are powerful sources of UV radiation, which can cause serious damage to unprotected eyes and skin. The accessory UV shield provides some UV protection; however, this shield does not protect others standing in the area around the imager. Specifically, when viewing around the UV shield at a distance of 20 cm, the measured Actinic UV emission is approximately 2.5 W/m², with a permissible exposure time of about 12 seconds; where even momentary exposure to Blue-light (300–700 nm) emission, when viewing without PPE at a distance of 20 cm, the measured Blue-light (300–700 nm) emission is approximately 1.5 W/m², with a permissible exposure time of about 60 seconds. Before performing band excision, the user and other lab personnel in proximity to the imager must put on protective gear including UV protective safety glasses, a face shield, lab coat, and gloves to ensure that no skin is exposed. A typical and reasonable expectation of use is three operations a day per user for three minutes each. Bystanders without protective gear must stand at least 1.5 meters (five feet) away from the imager and limit their exposure to no longer than one hour per day.

Important: Ensure anyone using the instrument wears approved personal protective equipment (PPE).

Important: Before excising bands, you must install the UV shield.


To install the UV shield

1. Pull out the transilluminator drawer.
2. Place a UV/Stain-Free Tray on the transilluminator drawer surface.
3. Place the shield over the tray:
 - a. Ensure the flap at the front of the UV shield is at a 90° angle.



- b. Insert the flap into the slot at the front of the drawer.

If the flap is inserted properly, the shield fits easily over the tray.



The UV lights turn off after 15 minutes of continuous use. To turn the UV lights back on, tap Turn Transilluminator On.

To excise bands on a UV/Stain-Free Tray

Important: Before you begin excising bands, ensure that you have on the required protective gear and that the UV shield is installed.

1. To avoid damaging the surface of the sample tray, place a sheet of clear glass or plastic on the tray before you add the gel sample.
2. Place a gel sample in the center of the tray.
3. In Camera view, tap Turn Transilluminator On.

The screen dims and the transilluminator lights turn on, illuminating the gel. The Turn Transilluminator Off button remains active, but all other screen options are not functional while the transilluminator is on.


Note: The UV lights turn on and the screen dims only when both the sample tray and the UV shield are in place. If the lights do not turn on, verify that the UV shield is installed correctly.

4. Raise the UV shield no more than is necessary to work with the sample.



Caution: Keep the UV shield open for as little time as possible.

5. Reach around the sides of the shield to excise the bands.



Caution: Sharp cutting tools can easily damage the surface of the tray. To avoid this, place a sheet of clear glass or plastic on the tray before you add the gel sample. Use a *chopping* motion rather than a *sawing* motion.

6. When you finish excising bands, tap Turn Transilluminator Off to turn off the UV lamps.
The screen no longer appears dim and the screen options become functional.
7. Remove the UV shield, remove the sample tray, and slide in the transilluminator drawer.

Excising Bands on a White Tray

Tip: Using the UV shield is not required when working with White Trays.



Caution: Sharp cutting tools can easily damage the surface of the trays. To avoid this, place a sheet of clear glass or plastic on the tray before you add the gel sample. Use a *chopping* motion rather than a *sawing* motion.

To excise bands on a White Tray

1. Open the transilluminator drawer and place a White Tray on the transilluminator.
2. Place a gel sample in the center of the tray.
3. In Camera view, tap Turn Transilluminator On.

The screen dims and the transilluminator lights turn on, illuminating the gel. The Turn Transilluminator Off button remains active, but all other screen options are not functional while the transilluminator is on.

Note: The lights turn on and the screen dims only when the sample tray is in place.

4. Excise the bands.
5. When you have finished excising the bands, tap Turn Transilluminator Off.

The screen no longer appears dim and the screen options become functional.

6. Remove the White Tray, and slide in and close the transilluminator drawer.

Excising Bands on a Blue Tray



Caution: Sharp cutting tools can easily damage the surface of the trays. To avoid this, place a sheet of clear glass or plastic on the tray before you add the gel sample. Use a *chopping* motion rather than a *sawing* motion.

Important: You must wear XcitaBlue goggles to see bands on a Blue Tray.


Note: Using the UV shield is not required when working with Blue Trays.

To excise bands on a Blue Tray

1. Open the transilluminator drawer and place the Blue Tray on the transilluminator.
2. Place a gel sample in the center of the tray.
3. In Camera view, tap Turn Transilluminator On.

The screen dims and the transilluminator lights turn on to 75% intensity. The Turn Transilluminator Off and Intensity level buttons remain active, all other screen options are not functional while the transilluminator is on.

Note: The lights turn on and the screen dims only when the sample tray is in place.



4. Tap the right or left Intensity arrows to change the brightness of the blue light coming from the transilluminator.

The intensity level increases or decreases by 5%. You can change the intensity from 50 to 100%. The system saves the selected intensity level for each user. Each time an individual user places a Blue Tray on the transilluminator, the system automatically defaults to the intensity level that the user last set. However, users can change the intensity level any time.

5. Excise the bands.
6. When you have finished excising the bands, tap Turn Transilluminator Off.

The screen no longer appears dim and the screen options become functional.

7. Remove the Blue Tray, and slide in and close the transilluminator drawer.

Chapter 8 Viewing Images

The Gallery displays thumbnails of all images you acquire, in order by the date of acquisition, most recent acquisition date shown first.


Note: Administrators can view all users' images at once or view an individual user's images.

Accessing the Gallery

To access the Gallery

- Tap Gallery in the main toolbar.

A Gallery similar to the following appears.



You can change the size of the thumbnails in the Gallery by tapping the plus and minus zoom icons on the right side of the Gallery screen.

The image name appears below each thumbnail image. By default, each name consists of the user name and the date and time of acquisition, for example: ChemiDoc Pro Admin 2025-03-10 11h15m56s.

You can change the file name in the Image Information box. You can also change the image name format.


See [Changing the File Naming Format on page 154](#).

Searching for Images in the Gallery

You can search for images of interest in the Gallery. Search text is not case sensitive. You can enter any part of the date or name. You can also search by application name or type.

To search for an image

1. Tap the search box to display the keyboard.



2. Enter search text. As you enter search text, images that match the search text appear in the Gallery.
3. Tap Done.

To return to a thumbnail view of all your images

- Clear the search box.

Selecting and Opening Images in the Gallery

To select an image

- ▶ Tap a thumbnail.

The selected image thumbnail appears outlined in blue and a check box appears in the upper right corner.


To open the selected image

- ▶ Double-tap the selected image to open it full size in Image View.

To open up to four images

- ▶ Select up to four images and tap View x Selected Images in the bottom toolbar, where x is the number of images selected.

The selected images appear outlined in blue, and with checkboxes selected.



To select all images you acquired on a single date

- ▶ Tap a date checkbox.

All images you acquired on the selected date appear outlined in blue, and with check boxes selected.

To select all of your images


- ▶ Tap Select All.

All images are selected and appear outlined in blue.

Note: You can only open up to four images at a time.

Sorting Images in the Gallery by Date

By default, the Gallery shows all images you acquired, starting with the last image acquired on the date you specify. When you acquire another image, the Gallery displays that image and all other images in the Gallery. You can filter the display by date to focus on images of immediate interest.



To filter images by date

1. Tap Show All in the image selection toolbar to open the dropdown list.
2. In the Date dropdown list that appears, tap one of the following.
 - **Date Range** — displays images acquired within a range of dates you specify. Tap the calendar boxes to specify dates in any order.
 - **Today** — displays images you acquired today starting at 12:00:00 AM and ending at 11:59:59 PM
 - **Yesterday** — displays images you acquired yesterday starting at 12:00:00 AM and ending at 11:59:59 PM.
 - **This Week** — displays images you acquired this week starting at 12:00:00 AM Sunday and ending at 11:59:59 PM the following Saturday.
 - **Last Week** — displays images you acquired starting at 12:00:00 AM Sunday last week and ending at 11:59:59 PM the following Saturday.
 - **This Month** — displays images you acquired this month starting at 12:00:00 AM of the first calendar day of the month and ending at 11:59:59 PM of the last calendar day of the month. For example, the month of January starts at 12:00:00 AM January 1 and ends at 11:59:59 PM January 31.
 - **Last Month** — displays images you acquired starting at 12:00:00 AM of the first calendar day of last month and ending at 11:59:59 PM of the last calendar day of last month.

Checking Intensity Values

In Image View, you can display the average intensity value and the percentage of saturation for any spot in an image. A 3 x 3-pixel region of the image is averaged, except at the edge or corner, where a 3 x 2 or 2 x 2-pixel region is averaged.

When viewing a multichannel image, you can check intensity values in any of the channel views or in the composite view.

Note: Hiding a channel in a composite image also hides the intensity values for that channel.


You can use the saturation percentage to estimate how much to increase exposure time to maximize the dynamic range of the image. For example, if the spot is 50% saturated, doubling the exposure time results in about 100% saturation. Viewing intensity values is also useful when comparing images.

To view intensity values in an image

1. In Image View, display an image.
2. Tap any spot in the image.

Intensity values for the selected spot appear.


Crosshairs mark the pixel area being evaluated. Intensity values fade out after a few moments.




To view intensity values in a composite image

1. In Image View, display a multichannel image.
2. Tap any spot in the composite image.

Color-coded intensity values appear for each channel in the composite image.




Crosshairs mark the pixel area being evaluated. Intensity values fade out after a few moments.



Viewing Multichannel Images in Image View

After a multichannel image is acquired, the composite image and its individual channel images appear in Image View. A blue border surrounds the selected image.



Images you open in the Gallery also appear in Image View. You can select and open up to four images at a time in the Gallery, all of which appear together in Image View.


To view more than one multichannel image at a time

1. In the Gallery, select the multichannel images you want to view.
2. In the lower toolbar, tap View x Selected Images, where x is the number of images you selected.

The multichannel images you selected appear in Image View.


To view an image full size

- Tap the expand arrows in the upper right corner of the image.



To view a single image in a multichannel image

- ▶ Tap the Previous and Next arrows at the lower right corner of each image.



Viewing a Composite or Merged Image in Grayscale

In Image View, you can view or export the composite or merged image in grayscale. In the Gallery, the thumbnail of the image also appears in grayscale. Channel colors of individual images are unaffected by the grayscale setting.


By default, a composite or merged image appears in Image View in RGB, the combined color settings of its channels.



To view the image in grayscale

- ▶ Tap the RGB toggle below the channel colors.

The toggle name changes to Gray and the image appears in grayscale.




Comparing Images


In the Gallery you can open and compare up to four images of a gel or blot at a time. The selected images appear in Image View.

To open multiple images

1. Select 1–4 images in the Gallery.
2. In the bottom toolbar, tap View x Selected Images, where x is the number of images selected.



The images you select in the Gallery open in Image View. By default, the top left image is selected.




Copying Image Settings


It is easier to compare images that have the same transform and zoom settings. You can copy these settings from one image to the others you selected.

To copy zoom settings from one image to the others

1. Select the image with the zoom settings you want to copy.



2. In the bottom toolbar, tap Copy Zoom.




The pan and zoom settings of the selected image are copied to the other images.

To copy transform settings from one image to the others

1. Select the image with the transform settings you want to copy.
2. In the bottom toolbar, tap Transform.



The transform settings for the selected image appear.



3. Tap Copy Transform in the transform settings box to copy the transform settings to the other images. Copy Transform only applies to the images that are visible on the screen. Channels that are not visible are not affected.

Viewing Image Information

The Image Information box provides information such as the image name, the acquisition's exposure duration and date, and the application type. Images with custom applications will also display the iris percentage (10%, 25%, 50%, and 100%), and the focus offset in centimeters.

To view information about the image

- In Image View, tap Image Info in the bottom toolbar.

The Image Information box appears, with the image information for the selected channel displayed. To see information for another channel in a multichannel image, tap that channel image and then tap the Image Info button.

Name

ChemiDoc Pro Admin 2025-12-04 14h00m06s

×

Notes

Acquisition Information

Imager	ChemiDoc Pro
Exposure Time (sec)	0.500 (Manual)
Instrument Name	Sim-CDPro-1
Serial Number	SIM-CDPRO-PM-1
Software Version	0.9.0.12180
Application	CustomApp
Excitation Source	Blue Epi Illumination
Emission Filter	590/110 Filter
Filter Info	[CHEZ Lens Distortion]
Focus Offset (cm)	2.0
Iris	25%
Flat Field	Applied (Blue Epi)

Image Information

Acquisition Date	12/4/2025 1:59:49 PM
User Name	ChemiDoc Pro Admin
Image Area (mm)	X: 210.0 Y: 139.8
Pixel Size (µm)	X: 69.8 Y: 69.7
Data Range (int)	628 - 24352

Images with custom applications will also display the iris percentage (10%, 25%, 50%, and 100%), and the focus offset in centimeters.

Name ChemiDoc Pro Admin 2025-10-08 11h02m47s ✕

Notes

Acquisition Information

Imager	ChemiDoc Pro
Exposure Time (sec)	0.500 (Manual)
Instrument Name	ChemiDoc Pro Instrument
Serial Number	SIM-CDPRO-MAIN-1
Software Version	0.9.0.11767
Application	Newest App
Excitation Source	UV Epi Illumination
Emission Filter	590/110 Filter
Focus Offset (cm)	2.0
Iris	100%
Flat Field	Applied (Orange (Epi))
Filter Info	[CHEZ Lens Distortion]

Image Information

Acquisition Date	10/8/2025 11:02:47 AM
User Name	ChemiDoc Pro Admin
Image Area (mm)	X: 210.0 Y: 139.8
Pixel Size (µm)	X: 67.0 Y: 67.0
Data Range (int)	628 - 24352

Note: For multichannel images with multiple custom applications, ChemiDoc Pro displays the focus offset and iris percentage of the first custom application in the composite image.


Viewing SAM Images

When SAM images are acquired, the last image acquired appears full size in Image View. You can view all the images in a SAM acquisition in the Gallery, where you can also rename, delete, or export the SAM group.


To select a SAM acquisition

1. Tap Gallery.


The Gallery displays the stacked SAM images in a thumbnail. The file name appears below the thumbnail. A stack icon in the bottom left corner identifies the thumbnail as a SAM acquisition.



2. Tap the SAM stack thumbnail.




The bottom toolbar displays the number of SAM images in the acquisition:




To view all images in a SAM acquisition

1. In the Gallery, tap the stack icon.



A thumbnail of each Image in the SAM acquisition appears.



To view a SAM image in Image View

- ▶ Double-tap a SAM image thumbnail.

The image you selected appears full size in Image View.


To view up to four SAM images in Image View

- ▶ Tap up to four SAM image thumbnails and then tap View x Selected Images in the bottom toolbar, where x equals the number of images you selected.

The selected images appear in Image View.

To restack SAM images

- ▶ Tap the SAM icon on any thumbnail in the SAM acquisition.



To clear a SAM image selection

- ▶ Tap inside a SAM image thumbnail.

To clear all image selections and restack the SAM images

- ▶ Clear the checkbox in any thumbnail and tap its stack icon.


Chapter 9 Merging Images

You can merge images to create multichannel images from up to three single images already acquired. For example, you can merge a colorimetric image of prestained standards and a chemiluminescent image of the same blot into a multichannel image. Original image data are not affected and can be used for quantitation as well as for determining the molecular weight or size of proteins. You can view merged images in grayscale. File names for merged images use the format specified in User > File Naming Preferences on the main toolbar.

Note: You cannot merge multichannel images. You cannot merge two or more SAM groups together, or merge a SAM group with a single image.


To merge images

1. In the Gallery, select up to three images.



2. On the lower toolbar, tap Merge.

The merged image appears in Image View.



To view merged image information

- On the Gallery lower toolbar, tap Image Info. In the Image Information box, detailed information about each image merged appears in Notes.

Name
0.00s Stain Free Blot 0.500s Stain Free Blot 0.500s

Notes

Merged Image
Channel 1: Chemiluminescence 0.500s
Acquisition Date: 1/26/2026 2:39:22 PM

Channel 2: Ponceau S 0.400s
Acquisition Date: 1/26/2026 2:38:51 PM

Channel 3: Stain Free Blot 0.500s-1
Acquisition Date: 1/26/2026 2:38:15 PM

Acquisition Information

Imager	ChemiDoc Pro
Exposure Time (sec)	0.500 (Manual)
Instrument Name	DSOTM11
Serial Number	ALPHA11
Software Version	0.9.0.12296
Application	Chemiluminescence
Excitation Source	No Illumination
Emission Filter	511/252 Filter
Binning	3x3
Flat Field	Applied (Lens Flat)

Image Information

Acquisition Date	1/26/2026 2:41:52 PM
User Name	admin
Image Area (mm)	X: 155.0 Y: 103.3
Pixel Size (µm)	X: 49.4 Y: 49.4
Data Range (int)	400 - 4008

Naming Merged Images

The system names the merged image by combining the application and exposure time for each image, and then appending the date the merged image was created.

If the name is already in use in the Gallery, the system generates another name by adding a hyphen and an incremental number (starting at 1) to the end of the combined name. The system continues to increase the added number incrementally (-2, -3, -4 and so on) until the name is unique.

To view the names of the source images

- ▶ With the merged image open in Image View, tap Image Info in the bottom toolbar.

In the Image Info box, the Notes section displays the names of the images that were merged.

Name	'5 0.500s Cy2 0.500s Chemiluminescence 0.500s	
Notes	Merged Image Channel 1: DyLight 550 0.500s Acquisition Date: 1/27/2026 1:29:16 PM Channel 2: Cy5 0.500s Acquisition Date: 1/27/2026 1:28:56 PM	

Chapter 10 Managing Images

Adding Notes to an Image File

To add information to an image file

1. In Image View, tap Image Info in the bottom toolbar.

The Image Information box appears.

The screenshot shows a modal window titled 'Image Information'. At the top, there is a 'Name' field containing the text 'brio 2025-03-11 11h11m57s' and a close button (X) on the right. Below this is a large, empty 'Notes' text area. The bottom half of the window is divided into two sections: 'Acquisition Information' and 'Image Information'. The 'Acquisition Information' section lists various parameters and their values, such as 'Imager: ChemiDoc Pro' and 'Exposure Time (sec): 4.435'. The 'Image Information' section lists details like 'Acquisition Date: 3/11/2025 11:11:57 AM' and 'User Name: brio'.

Acquisition Information	
Imager	ChemiDoc Pro
Exposure Time (sec)	4.435 (Optimal Auto-exposu...
Instrument Name	SIM-CDPRO-MAIN-1
Serial Number	SIM-CDPRO-MAIN-1
Software Version	0.9.0.11035
Application	SYPRO Ruby
Excitation Source	UV Trans Illumination
Emission Filter	590/110 Filter
Flat Field	Applied (Orange)

Image Information	
Acquisition Date	3/11/2025 11:11:57 AM
User Name	brio
Image Area (mm)	X: 106.6 Y: 71.0
Pixel Size (µm)	X: 35.4 Y: 35.4
Data Range (int)	100 - 3115

2. Tap in the Notes box.
3. Enter your notes using the on-screen keyboard.
4. Tap the keyboard key on the lower row of the keyboard to close the keyboard.

The notes you type are automatically saved.

For more information, see [Viewing Image Information on page 144](#).

Changing the File Naming Format

By default, the file name consists of the elements user name, date, and time. In the File Naming Preference dialog, you can change the file naming format at any time.


- You can remove an element and replace it with another element.
- You can include the Text element, which holds up to 32 alphanumeric characters.
- You can reorder the elements.

To change the file naming format, you can select up to four of the seven elements in the File Name Elements List and arrange them in the order you prefer.


Tip: The File Name Elements list includes a combination element, App/Exposure, which is useful when you want to include more than four kinds of information in the format.

To change the file name format

1. Tap User Settings, and then tap File Naming.



The File Naming Preference dialog appears. Default elements are User Name, Date, and Time.



2. Do one or both of the following:
 - To remove an element from the file name pattern, drag an element from the format onto the File Name Elements list.
 - To add an element to the file name pattern, drag an element from the File Name Elements list onto an empty position.

An example of the file name in progress appears as you select each element.

3. Repeat Step 2 as applicable.
4. Tap OK to save the format.

The software names all images you acquire using the new file naming pattern.

Renaming Images

When you acquire an image, the system assigns it a default name. You can change this name in Image View or in the Gallery. In the Gallery, you can also save a series of images with the same name plus an incremental number. Doing so makes it easy to find related images.

An image name can consist of up to 190 alphanumeric characters. Spaces are permitted except at the beginning and end.

Note: The following characters cannot be used: \ / : * ? " < > |

To rename an image in the Gallery

1. Select an image.
2. Tap Rename in the bottom toolbar.
3. In the Rename dialog, enter a name for the image.
4. Tap OK.

To rename multiple images in the Gallery

1. Select more than one image.
2. Tap Rename.
3. In the Rename dialog, enter a name for the first image.
4. Tap OK.

The system labels the remaining images with the same name as the first image plus a consecutive number. For example: ChemiBlot_1, ChemiBlot_2, and so on.

To rename an image in Image View

1. In Image View, tap Image Info.
2. In the Image Information box, tap in the Name box to select the image name.
3. Type a new name.
4. Tap OK to save the image name.

Renaming SAM Images

You can rename a SAM image or a SAM group. You can rename a combination of single SAM images, SAM groups, and other images. Image and group names must be unique.

When you rename a SAM group each image in the group is also renamed. An underscore and a sequential number are added to each image name to render it unique. The oldest SAM group or image is assigned the first sequential number. The remaining images are assigned sequential numbers, oldest image first.

Example

You select a SAM group, SAM 8497, and another image in the Gallery.

You rename SAM 8497 to SAM 9001.


The first image acquired is named SAM 9001_1. The remaining images (including the image that is not in the SAM group) are renamed SAM 9001_2, SAM 9001_3, SAM 9001_4, and so on, in the order in which they were acquired. If the image outside the SAM group was acquired before the acquisition of the SAM group, that image is renamed SAM 9001_1. In this case, the SAM group is renamed SAM 9001_2. The remaining images are renamed SAM 9001_3, and so on, in the order in which they were acquired.

To rename a SAM image

1. Tap the SAM stack thumbnail.
2. Select a SAM image.
3. Tap Rename in the bottom toolbar.
4. Enter a name in the Rename Image dialog and then tap OK.

To rename all images in a SAM group

1. Restack the SAM images.
2. Tap the SAM stack icon.
3. Tap Rename.
4. Enter a name in the Rename Image dialog and tap OK.



Printing Images

You can print one image at a time on the Sony UP-X898MD printer only. The printer produces a black and white image in landscape orientation. The printout includes the user name, acquisition date and time, and the application used. You can zoom the image and print the portion of the image within the view, or you can print the entire image. For more information about the printer, see its operation manual.

To print an image

1. Ensure that the printer is connected to the imager and is turned on.
2. In Image view, display the image you want to print.
3. (Optional) Zoom into the portion of the image that you want to print.
4. Tap Print.
 - Tap Current View to print the portion of the image within the view.
 - Tap Entire Image to print the complete image.

Deleting Images

In Image View, you can delete any open image. In the Gallery, you can delete multiple images at the same time.

To delete images in the Gallery

1. Do one of the following to select images to delete:
 - Tap one or more thumbnails.
 - Tap the checkbox for one or more days to select all thumbnails for those days.
 - Tap Select All to select all thumbnails in the Gallery.
2. Tap Delete and then tap OK.

To delete an image in Image View

1. Do one of the following:
 - If one image is open in Image View, tap Delete.
 - If more than one image appears in Image View, select the image you want to delete.
2. Tap Delete and then tap OK.

Deleting SAM Images

Tip: You can delete SAM images in the Gallery or in Image View.

In the Gallery, you can delete

- A SAM image or a SAM acquisition
- A combination of single SAM images, SAM acquisitions, and other images

In Image View, you can delete

- A full size image
- An image you select from a view of up to four images

To delete images from a SAM acquisition in the Gallery

1. Tap the stack icon next to a SAM stack thumbnail.
2. Tap the thumbnail of one or more SAM images you want to delete.
3. Tap Delete in the bottom toolbar.
4. To confirm deleting the images permanently, tap OK.

To delete a SAM acquisition in the Gallery

1. Restack the SAM images.
2. Tap inside the SAM stack thumbnail.
3. Tap Delete in the bottom toolbar.
4. To confirm deleting the images permanently, tap OK.

To delete a combination of SAM images, other images, and SAM acquisitions in the Gallery

1. Tap the stack icon next to each SAM acquisition that contains images you want to delete.
2. Tap the SAM image thumbnails, non-SAM images, and SAM acquisitions you want to delete.
3. Tap Delete.
4. To confirm deleting the images permanently, tap OK.

To delete a SAM image in Image View

1. Do one of the following:
 - If one SAM image appears in Image View, tap Delete.
 - If more than one image appears in Image View, select the image you want to delete and tap Delete.
2. To confirm deleting the image permanently, tap OK.


Chapter 11 Exporting Images

After acquiring images using Image Lab Touch Software, you can view and analyze your images in BR.io or the Bio-Rad desktop software Image Lab Desktop Software.

You can export acquired images directly to the Bio-Rad cloud application BR.io to view the image details and to analyze the image. For more information on image details and analysis, see the BR.io help. You must link the instrument to your BR.io account. See [Linking to Your Bio-Rad BR.io Account on page 52](#) for information about creating an account and linking your imager to the account.

To export to Image Lab Desktop Software, first export the acquired images to a USB drive or a shared network folder. Then copy the exported images to a computer running Image Lab software. For more information about image analysis, see the Image Lab Software User Guide.

You can export a SAM group or individual SAM images. You can also export a combination of single SAM images, SAM groups, and other images. SAM images and groups are stored in a folder inside the top-level time-stamped folder:



You can export images from the imaging system to one of the following:

- BR.io

Note: You can export all four channel images to BR.io.

- Image Lab Touch Software via USB drive or shared folder on a network drive or stand-alone computer

Note: You can export up to three channels as a multi-channel image (RGB), or four channels as four single channel images (R, G, B, Gray) to Image Lab Desktop via a USB drive or shared network drive or standalone computer.

- Attached USB drive. These files export as four separate single-channel (.scn) files—one for each channel (R, G, B, and Gray)
- Shared folder on a network drive or stand-alone computer. These files export as four separate single-channel (.scn) files—one for each channel (R, G, B, and Gray)

Image Lab Touch Software exports the images to a folder at the top level of the selected location. The folder is named *ChemiDoc Pro System Images* plus a time stamp, for example, *ChemiDoc Pro System Images 2025-04-01_15.11.29*. A folder with a time stamp is created each time you export images.

Automatically Exporting Images

If you have a BR.io account and are linked to BR.io, you can choose to automatically export images, including SAM images, to your account. For more information about setting up Image Lab Touch Software to automatically export to BR.io, see [Automatically Exporting to BR.io on page 172](#)

Alternatively, administrators can choose to export all images a shared network location. This feature is particularly helpful in a restricted environment. All images taken by all users are automatically exported to a specific network location. For more information, see [Setting Administrator Options on page 57](#).

Auto-Upload Status Icons

Images that are automatically exported to BR.io or a shared network drive display an icon that indicates the status of the export. [Table 15](#) lists the icons and explains their status.

Tip: Tapping the icon on images that fail to auto-upload displays a dialog that explains the reason for the failure.

Table 15. Icons on Auto-Exported Images.

Icon	Status
	Auto-upload to BR.io is in progress.
	Auto-upload to BR.io succeeded.
	Auto-upload to BR.io failed.
	Auto-upload to a shared network drive is in progress.
	Auto-upload to a shared network drive succeeded.
	Auto-upload to a shared network drive failed.

Exporting Images

You can export both single-channel and multichannel images to a shared network drive, an attached USB drive, or Bio-Rad's cloud application BR.io. Multichannel (RGB) images exported to a network or USB drive can include up to three channels. If an image contains four channels, the system exports it as four separate single-channel files—one for each channel (R, G, B, and Gray).


Before you export to BR.io, you must set up a BR.io account and then link your ChemiDoc Pro System imager to your BR.io account.

Before you can export images to a network, a shared folder must be present on the destination network, and you must know the UNC path to the shared folder.


You can export images from the Gallery or from Image View.

To export images

1. Do one of the following:
 - Select one or more images in the Gallery to export.




- Display up to four images in Image View and select an image to export.



2. Tap Send/Save on the bottom toolbar.


The available export locations appear on the top half of the screen.



3. Select a target location.
4. Under Export Options, choose the file formats in which you want to export the images.

Note: If you select Send to BR.io, you can only export to Image Lab format. If you select any other option, Send to BR.io is disabled.

A progress box monitors the export.



5. When the export finishes, tap OK.

Export Formats

You can export images to display them in a presentation, submit them for publication, to a computer running Image Lab Software, or to your BR.io account to analyze them in more detail. Using Image Lab Software you can analyze the images or set additional publication options. For more information, see the Image Lab Software User Guide.


In Image View, you can export one image at a time. The software exports the current view of the image when a publication format is selected. In this view, zooming and panning are considered.

In Gallery View, you can export multiple images at the same time. The software exports the full size of the images in all selected formats.

Choosing Export Formats

To help you identify exported images the software appends application name in parentheses to the end of the file name. This is especially helpful for multichannel images.

Example



[Table 16 on page 169](#) lists the file formats into which you can export images.

Export File Formats

Table 16. Export file formats.

Export Option	File Extension	Description
Image Lab	.scn or .mscn	Important: Only images in Image Lab format are sent to BR.io. By default, Image Lab is selected. Image Lab Touch Software exports a single-channel image in .scn format or a multichannel image in .mscn format. To work with images in Image Lab software, use these formats.
Publication	.tif or .jpg	Important: Images in Publication format are not sent to BR.io. To send images to BR.io, select Image Lab format. Image Lab Touch Software exports the current view of an image in .tif or .jpg format at 300 DPI, which is suitable for publication. You can also insert an image in .tif or .jpg format into presentation software such as Keynote or PowerPoint. Tip: Additional publication options are available in Image Lab Software. For example, in Image Lab you can export an image at up to 1200 DPI. To set these publication options for the image, export the image in the .scn or .mscn format, open the file in Image Lab, set the options, and export the image in .tif or .jpg. Note: In a multichannel acquisition, the composite image is exported as shown in the Image View and/or Gallery View using the composite view options (channel selection and gray/RGB color selection).

Export Option	File Extension	Description
Analysis	.raw.tif	Important: Images in Analysis format are not sent to BR.io. To send images to BR.io, select Image Lab format. Image Lab Touch Software exports 16-bit .tif format (raw16.tif), which retains original pixel intensity data from the image acquisition. This raw image data enhances quantitative analysis. You can also use this format to import the image into image editing software that supports the 16-bit .tif format. Note: You cannot export a composite image from a multichannel acquisition in .raw16.tif format.

Exporting to BR.io

Note: Only images in Image Lab format are exported to BR.io. If you select another format type, Image Lab Touch Software displays a message with this information and prompts you to send to BR.io or cancel. If you select Send, your image is exported to BR.io in Image Lab format.

You can manually export individual images to BR.io or choose to automatically export every image to BR.io. When enabled, all images you scan are automatically exported to your BR.io account including merged images and secure images.


Note: Your administrator can choose to have all images automatically exported to a shared network. You cannot change this setting.

Important: Images that are automatically exported cannot be renamed or deleted. Additionally, you cannot add notes to the Notes text box for images that are automatically uploaded.

Manually Exporting Images to BR.io

To manually export individual images in the Gallery to BR.io

1. Confirm that you have a BR.io account and that your ChemiDoc Pro System imager is linked to your account.
2. From the Gallery, select the image or images you want to export.
3. Tap Send/Save on the bottom toolbar.
4. Tap Send to BR.io.
5. Ensure that Image Lab is selected option.



A progress box monitors the image export.

6. When the export finishes, tap OK.

To manually export an image in Image View to BR.io

Note: In Image View, you can export only one image at a time to BR.io.

1. Double-tap an image to display it in Image View.
2. Tap Send/Save on the bottom toolbar.
3. Tap Send to BR.io.
4. Ensure that Image Lab is selected.

A progress box monitors the image export.


5. When the export finishes, tap OK.

Automatically Exporting to BR.io

When Auto Send to BR.io is enabled, all image scans that you take are automatically exported to your BR.io account.

To automatically export images to BR.io

1. Confirm that you have a BR.io account.
2. On the main toolbar, tap User Profile to open the BR.io Account dialog.
3. Select Auto Send to BR.io.



4. Close the BR.io Account dialog.

To cancel automatically export images to BR.io

- To cancel automatic image export to BR.io, clear the checkbox in the BR.io Account dialog.

Exporting to a USB Drive or External Hard Drive

The USB drive or external hard drive must meet the following requirements:

- Supports USB 2.0 or above
- Formatted with exFAT, FAT32, or NTFS format
- Has no encryption software or other software add-ons on the drive

Note: USB drives formatted as exFAT or FAT32 export files much more quickly than USB drives formatted as NTFS. If your USB export takes too long, reformat the USB drive as exFAT or FAT32.

To export images in the Gallery to a USB drive or external hard drive

1. Connect a USB drive or an external hard drive to the imaging system's USB port.
2. From the Gallery, select the images you want to export.
3. Tap Send/Save on the bottom toolbar.
4. Select export options.
5. Tap Save to USB Drive.

A progress box monitors the image export.

6. When the export finishes, tap OK.

To export an image in Image View to a USB drive or external hard drive

Note: You can export only one image at a time in Image View.

1. Double-tap an image to display it in Image View.
2. Connect a USB drive or an external hard drive to the imaging system USB port.
3. Tap Send/Save on the bottom toolbar.
4. Select export options.
5. Tap Save to USB Drive.

A progress box monitors the image export.

6. When the export finishes, tap OK.

Preparing to Export Images to a Shared Folder

Before you can export images to a stand-alone computer, a shared folder must be present on the computer, and you must provide the UNC path to that folder.

The UNC (universal naming convention) is a standard for identifying servers and computers on a shared network. It is the full network path name of a folder, including the network server name. This path is the same as a Windows folder path except that it uses double backslashes (\\) to precede the name of the computer.

Note: The procedures for determining the UNC path and creating a shared folder on it are based on recent versions of Windows and Mac operating systems. If your computer is running on a different operating system version, you might notice differences in the user interface.

Creating a Shared Folder on a Windows Computer


This section explains how to create a shared folder on a Windows computer and how to determine its UNC.

Note: In order to export images to a Windows computer, ensure that the imaging system is connected to the stand-alone computer or to the network port by Ethernet cable.

To create a shared folder on a Windows computer

1. Log in as the Windows Administrator for the computer.
2. Create a destination folder.
3. Right-click the folder and select Properties in the menu that appears.
4. Click the Sharing tab in the Properties dialog.


5. Under Network File and Folder Sharing, click Share.



6. Choose users with whom you want to share the destination folder.
7. Click Share and then click Done.
8. (Optional) Set Read/Write permissions for each user.
9. Click Close.

To determine the UNC path to the shared folder

1. On the Sharing tab, in the Network Files and Folder Sharing section the UNC path appears under Network Path.



2. Write down this path. You will enter this address when you export an image.

Creating a Shared Folder on a Mac Computer

This section explains how to create a shared folder on a Mac computer and how to determine its UNC.

Tip: The UNC for a Mac computer includes its Apple Filing Protocol (AFP) or Server Message Block (SMB).


Note: In order to export images to a Mac computer, ensure that the imaging system is connected to the stand-alone computer or to the network port by Ethernet cable.

To create a shared folder on a Mac computer


1. Log in as the Administrator.
2. Create a destination folder.
3. Click the folder and choose Get Info in the menu that appears.

The <folder name> Info dialog appears.

4. Select Shared Folder.



5. On the Apple menu, open System Preferences and select File Sharing in the Sharing dialog.
6. In the Sharing & Permissions box, verify that the users with whom you want to share the folder have permission to read and write to this folder.



7. In the Service pane, select File Sharing.
8. Under File Sharing: On, locate the SMB address and write it down.
You will enter the SMB address when you export an image.
9. Click Options.
10. In the dialog that appears, select Share files and folders using SMB.

You can select both SMB and AFP. By default, OS X Mavericks and later systems automatically enable SMB and AFP for compatibility with Windows computers, Macs using Mavericks and Yosemite, and Macs using older versions of OS X. For more information about compatibility with later Mac operating systems, contact Apple support.



11. Click Done.

Determining the UNC of a Previously Shared Folder

In order to export images to a computer, you must provide the UNC path to the folder. This section explains how to determine the UNC of a folder that has already been shared on Windows or Mac computer.

Determining the UNC Path to a Network Folder on a Windows Computer

If the folder is located on a mapped network drive, you will need to determine the path to that drive as well. Mapped network drives appear in Windows Explorer as simulated drives. This is indicated by a drive letter, for example (H:). This section also explains how to determine the path to a mapped network drive on a Windows computer.

To determine the UNC path to network folder on a Windows computer

1. Log in as the Windows Administrator for the computer.
2. In the Navigation pane, click the Network icon and navigate to and select the destination folder.

The address bar displays the network path to the destination folder, beginning with the word Network.

3. Click the address bar. Then UNC path appears in the address bar, for example:

\\ImagesForEval

4. Write down this path. You will enter this address when you export an image.

To determine the path to a mapped drive

1. Log in as the Windows Administrator for the computer.
2. In the Navigation pane, click the network folder that contains the destination folder.

The address bar displays the mapped network path to the destination folder, beginning with the word Computer, for example:

Computer > ILTuser (\\usherfs\users) (H:) > ImagesForEval

3. To construct the UNC path, follow this rule:

\\<shared_folder_name>\mapped_foldername\destination folder

In this example

- \\usherfs\users — is the shared folder location
- ILTuser — is the mapped folder name

- ImagesForEval — is the destination folder

For example:

\\usherfs\users\ILTuser\ImagesForEval


Determining the UNC Path to a Network Folder on a Mac Computer

Tip: The UNC for a Mac computer includes its Apple Filing Protocol (AFP) or Server Message Block (SMB).

Note: In order to export images to a Mac computer, ensure that the imaging system is connected to the computer or to the network port by Ethernet cable.

To determine the UNC path to a network folder on a Mac computer

1. Log in as the Administrator.
2. On the Apple menu, open System Preferences and select File Sharing in the Sharing dialog.



3. Note the AFP or SMB path that appears below File Sharing: On. In this image, the SMB is 10.2.53.37.

This is the computer's IP address, which is used to determine the computer name in the UNC path.

4. To construct the UNC path, follow this rule:

`\\SMB #\Users\<user_name\<folder_name\`

In this example

- 10.2.53.57 — is the SMB
- Tester — is the user name
- CDT Export — is the folder name

For example:

`\\10.2.53.57\Users\Tester\CDT Export`

Exporting to a Shared Folder for the First Time

Note: The following characters are not supported in paths to shared folders: * ? " < > | ;


When you enter a path that includes an unsupported character, an error message appears. Folder names that include unsupported characters cannot be selected in browse results. You can rename the shared folder to exclude the unsupported character or choose another folder that does not include one of these characters in its name.

Before exporting images to a shared folder on a network drive or a stand-alone computer for the first time, obtain the following information:

- The UNC path to the shared folder on the network drive or stand-alone computer
- Log-in credentials to the shared folder

To export images to a shared folder

1. Verify that the imager is connected via an Ethernet cable to a network outlet or to a stand-alone computer.
2. Do one of the following:
 - Select the images you want to export in the Gallery.
 - Go to Image View by acquiring an image or by opening an image in the Gallery.
3. In the bottom toolbar, tap Send/Save.
4. Select Export Options.



5. Tap Save to Network.

The Save to Network dialog appears.

6. Type the pathname to the shared folder on the network drive or stand-alone computer.

Enter the network drive server name or IP address.

Server name pathname format: `\\ServerName\Share1\Path\To\Folder`

Example: `\\BioServer1\Share1\Images\Experiment1`

IP address pathname format: `\\IPAddress\Share1\Path\To\Folder`

Example: `\\10.1.52.162\Share1\Images\Experiment1`

7. Tap Save.
8. If a log-in dialog appears, enter the log-in credentials to the shared folder. For a network drive, enter the network domain name, your user name on the domain, and your password in this form:

domain_name\username\password

Example: **Global.xyz.com\jdoe**

9. Tap OK.

A progress bar monitors the image export. When the export finishes, tap OK.

Exporting to a Shared Folder on a Network or Computer

Note: The following characters are not supported in paths to shared folders: * ? " < > | ;

When you enter a path that includes an unsupported character, an error message appears. Folder names that include unsupported characters cannot be selected in browse results. You can rename the shared folder to exclude the unsupported character or choose another folder that does not include one of these characters in its name.

Note: You cannot export more than three channel images (RGB) to a USB drive or external hard drive.

Entering Log-in Credentials

When you export an image to a shared folder on a network drive or a stand-alone computer, you must enter log-in credentials. After you connect to a shared folder, the connection remains active until you log out.


Before you export images to a shared folder, obtain the following information:

- The UNC path to the shared folder on the network drive or stand-alone computer.
- Log-in credentials to the shared folder

If you do not have write permission to the shared folder, see your system administrator for write permission.


To export images to a shared folder

1. Verify that the imager is connected via an Ethernet cable to a network outlet or to a stand-alone computer.
2. Do one of the following:
 - In the Gallery, select one or more images to export.
 - In Image View, display an image to export.
3. Tap Send/Save in the bottom toolbar.
4. Select export options.
5. Tap Save to Network and then tap Browse.



6. Do one of the following:
 - Enter the UNC path name to the shared folder on the network drive or stand-alone computer.
Tip: This is the path name you noted when you set up the shared folder. See either [Determining the UNC Path to a Network Folder on a Windows Computer on page 180](#) or [Determining the UNC Path to a Network Folder on a Mac Computer on page 181](#).
 - Tap the path name you want under Save in the Save to Network dialog.
7. Tap Connect.

If you are not connected to the network drive or computer, the system prompts you for log-in credentials.



8. Enter the log-in credentials to the shared folder and then tap OK.

For a network drive, type the network domain name, your user name on the domain, and your domain password in this form:

domain_name\username

user password

9. Tap Save to Folder. A progress box monitors the image export.
10. When the export finishes, tap OK.


Exporting to a Recent Location

When you export images to a shared folder on a network drive or stand-alone computer, the software saves the location you enter. The next time you export an image, the Save to Network dialog displays the ten most recent locations you entered, most recent location first.

To export images to a recent location

1. Verify that the imager is connected via an Ethernet cable to a network outlet or to a stand-alone computer.
2. In the Gallery or in Image View, select the images you want to export.
3. Tap Send/Save in the bottom toolbar.
4. Select export options.
5. Tap Save to Network.

The Save to Network dialog appears.



6. Tap a shared folder in the recent locations list and then tap Save to Folder.

A log-in dialog appears if the connection to the network drive or stand-alone computer is not active.

7. Enter the log-in credentials to the shared folder.

To enter the log-in credentials for a network drive, type the network domain name, your user name on the domain, and your domain password. Type the domain and user name in this form:

domain_name\username

for example: **Global.xyz.com\jsmith**

8. Tap OK.

A progress box monitors the image export.

9. When the export finishes, tap OK.

Removing Network Locations

To remove network locations from the list

- ▶ Tap a location and then tap Remove.

Disconnecting from a Shared Folder

The imaging system remains connected to a shared network folder until you log out or turn off the imaging system or until the network disconnects you.

Chapter 12 System Settings

The System Settings menu displays options that can be changed on the imager. Users can view information about the imager and change the system sound level when they log in.

Administrators can also set the following options for the imager:

- Instrument name
- Instrument standby
- Date and time
- Time zone
- Language from English (the default) to Simplified Chinese
- Network connection

This chapter explains how to set these options.


Setting the Instrument Name

Users can change the ChemiDoc Pro System instrument name so that it is easier to find in BR.io.


Note: If a user is assigned an Admin role, the Admin can change the instrument name.

To set the instrument name

1. Tap Settings in the main toolbar, and then tap Instrument Name...



2. Using the alphanumeric keyboard that appears, enter the new instrument name.



Note: The instrument name is limited to 32 characters and cannot contain the characters \ : * ? " < > | or start or end with a space.

3. Tap OK.
4. The ChemiDoc Pro System instrument name is changed and appears in the main toolbar. The new instrument name also appears on the Welcome Screen, the About This Imager... dialog, and in an image's information section.

Instrument Standby Settings

Users can configure the ChemiDoc Pro System instrument to enter standby mode to save energy. The instrument can automatically enter into standby mode after 5, 10, 15, or 30 minutes, or one hour of inactivity.


After the instrument enters standby mode, the monitor turns off, the cooled camera is set to a standby temperature, and the LED indicator by the front power button pulsates blue. The imager exits standby mode and displays the home window when a user interacts with the touch screen. If the imager is locked, the lock screen appears with the name of the logged-in user.

Users can also manually set the instrument to standby mode by clicking the Standby button in the Log Out dialog. For more information, see [Standby Mode on page 42](#)


To configure the standby timeout time

1. Tap Settings in the main toolbar.

Tap Standby... in the list that appears.



2. Select the radio button for the idle time before the instrument enters standby.



3. Tap X to close the list.

Note: The imager logs the current logged-in user out when it enters standby mode, unless the logged-in user locks the instrument. For more information on locking the instrument see [Locking the System on page 40](#).

Setting the System Date, Time, and Time Zone

Before you begin to work with the imaging system, verify that the date and time settings are correct for your locale.

Note: The date and time appear in the default names assigned to acquired images.


If your instrument is connected to a network you can enable the automatic date and time setting, which synchronizes your system with the date and time information from an NTP server for your geographic location.

You can also set a particular date and time by selecting a specific time zone. Additionally, administrators can change the NTP server or add multiple servers.

If your instrument is not connected to a network, you can manually set the date and time.

To automatically set the date and time

1. Tap Settings in the main toolbar, and then tap Date and Time...



2. Select the Set date and time automatically check box, and then tap OK.

Set Date To: Wednesday, January 28, 2026

Set Time To: 12:18 PM

January 2026						
S	M	T	W	T	F	S
28	29	30	31	1	2	3
4	5	6	7	8	9	10
11	12	13	14	15	16	17
18	19	20	21	22	23	24
25	26	27	28	29	30	31
1	2	3	4	5	6	7

☐ Set date and time automatically

NTP Server... OK Cancel

By default, Image Lab Touch Software sets the date and time based on NTP.

Important: When the checkbox is selected, you cannot manually change the date and time.

To change the NTP server or add additional NTP servers

1. Tap Settings in the main toolbar, and then tap Date and Time...
2. Tap NTP Server...

Important: The Set date and time automatically checkbox must be selected to enable the NTP Server... button.

3. In the NTP Server dialog, enter the new server name(s) using the alphanumeric keypad.


Note: Separate multiple NTP servers by a space. Leave this field empty to use the default server.

Note: Server names cannot contain the characters \ : * ? " < > | or start or end with a space.


4. Tap OK.

To set the system time zone

1. Tap Settings in the main toolbar, and then tap Time Zone...




2. From the Select New Time Zone list, scroll to find the time zone for your locale.



3. Tap the time zone to select it and then tap OK.

To manually set the current date and time

1. Tap Settings in the main toolbar, tap Date and Time... in the list that appears.
2. Ensure the Set date and time automatically check box is cleared.
3. In the Calendar box, tap the angle brackets to display the current month.



4. Tap the day of the month.
5. Scroll through the Hour and the Minutes lists until the current time appears in the blue band.
6. Scroll to position AM or PM in the blue band under AM/PM.

7. Tap OK.

The selected date and time appear at the top of the all Image Lab Touch Software screens.

Setting the System Language


Note: Only those with the administrator role can change the system language.

You can change the system language from English language to Simplified Chinese. Image Lab Touch Software will display all on-screen text in the selected language. It will also display the on-screen keyboard in the selected language.

Tip: You can choose to display the on-screen keyboard in either English language or Simplified Chinese without changing the system language. See [Using the On-Screen Keyboard on page 36](#) for more information.

To set the system language

1. Tap Settings in the main toolbar.
2. Tap Language... in the list that appears.




3. Tap the appropriate language.
4. Tap X to close the list.

Setting the Sound Volume

You can change the system sound volume or turn off the sound.

To set the sound volume

1. Tap Settings in the main toolbar.
2. Tap Sound Volume... in the list that appears.



3. Tap a volume level.
4. Tap X to close the list.

Configuring the Network Connection

Note: Only those with the administrator role can configure the network connection.

The ChemiDoc Pro System can connect to your internal network using either a static or dynamic IPv4 connection, or using a Bio-Rad-supplied Wi-Fi adapter.

When logging in to ChemiDoc Pro System, the Welcome screen displays an icon in the lower left corner that identifies whether the instrument is connected to the internal network and by which connection type. [Table 17](#) that follows displays the different icons that users will see on the Welcome screen.

Table 17. Network connection icons.

Icon	Connectivity Type
	Ethernet connection
	Wi-Fi connection
	No network connection

This section explains how to configure the network connection using either Ethernet or Wi-Fi connection.

Setting Up an Ethernet Connection

Note: Only those with the administrator role can configure the network connection.

The ChemiDoc Pro System can connect to your internal network using either a static or dynamic IPv4 connection.

By default, the ChemiDoc Pro System's IP connection is dynamic. That is, the IP address can change each time the imager restarts. In these cases, the imager automatically establishes a new connection to the network each time it starts. A static IP address never changes, thus the imager always reconnects to the same network address each time it restarts.

This section explains how to view the dynamic or static IP networks settings, and how to set the network connection.

Tip: If you choose to set a static connection, you might need the assistance of your system administrator for specific network settings.

Important: You must restart the imager to apply the changes.

Note: Before starting this procedure, ensure your ChemiDoc Pro System imager is turned off.

To set up the network connection

1. If you have not already done so, insert one end of the provided Ethernet cable into the Ethernet port on the back of the ChemiDoc Pro System imager.
2. Insert the loose end of the cable into the network connection router or hub.
3. Turn on the imager.
4. Log into the ChemiDoc Pro System imager as an administrator.

The ChemiDoc Pro System imager automatically detects an available IP address and connects to your network. The imager displays the Ethernet icon on the lower left of the Welcome screen to indicate successful Ethernet network communication.



5. Tap Settings in the main toolbar.
6. Tap About This Imager ... in the list that appears. The imager's information screen appears, for example:


Image Lab Touch Software		✕
© 2026, Bio-Rad Laboratories, Inc.		
Software Version:	0.9.0.13714 CI GC-33c53fa4	
Instrument Type:	ChemiDoc Pro	
Instrument Name:	ChemiDoc Pro	
Serial Number:	ALPHA11	
Firmware Version:	1.4.079.1	
Camera Serial Number:	ALPHA11	
Camera Firmware Version:	1.4.079.1	
Disk Image Version:	Bio-Rad ChemiDoc Pro OS Development 0.9.10	
BR.io Service Version:	0.9.0.29	
Network Connections:	10.2.227.43 (IPv4) fe80::36c9:f0ff:fe90:6f96%wlu1u4 (IPv6)	
MAC Address:	34:C9:F0:90:6F:96	
Disk Space Free:	93% (869,045 MB)	

7. Write down the IPv4 address located in the Network Connections section. You will need this number to set a static connection.
8. Tap X to close the system information screen.

Setting Up a Static IP Network Connection

When setting up a static IP network connection, you must provide the IPv4 address, subnet mask, gateway and DNS server details for your system. See your system administrator for the appropriate settings.

1. Ensure that you have properly inserted the provided Ethernet cable into the imager and that it is connected to the network connection router or hub.
2. Tap Settings in the main toolbar.
3. Tap Network Configuration...



4. On the Network Configuration screen, tap Ethernet.
The IPv4 Properties dialog appears.

Internet Protocol Version 4 (TCP/IPv4) Properties ✕

You can get IP settings assigned automatically if your network supports this capability. Otherwise, you need to ask your network administrator for the appropriate IP settings.

☒ Obtain an IP address automatically

☐ Use the following IP address: _____

IP address: . . .

Subnet mask: . . .

Default gateway: . . .

☒ Obtain DNS server address automatically

☐ Use the following DNS server addresses: _____

Preferred DNS server: . . .

Alternate DNS server: . . .

OK Cancel

5. If your network supports a dynamic connection, tap the following options:

- Obtain an IP address automatically
- Obtain DNS server address automatically


Note: Automatically assigning an IP address will use a Link-Local address if a DHCP server is not on the network.

6. To set a static connection, tap Use the following IP address and Use the following DNS server addresses options and then provide the IP address, subnet mask, default gateway, and DNS server details for your site.

Tip: See your system administrator for the appropriate settings.

- IP address — the IPv4 number that you noted on [Step 7](#) in [To set up the network connection](#)
- Subnet mask — the numeric filter used to define the subnet to which the IP address belongs

- Default gateway — (required if you plan to access computers that are on a subnet other than the one on which the Imaging System belongs) this is the IP address of the node that allows communication between the subnets
 - DNS server — the IP address of the node that translates a server name to its IP address
7. Tap OK to save the changes.
 8. Tap X to close the dialog.
 9. The system displays the Ethernet icon in the lower left corner of the Welcome screen to indicate successful Ethernet network connection.



10. If necessary, implement network security measures per your organization's security and privacy policies.

Setting Up a Wireless Connection

Note: The ChemiDoc Pro System Wi-Fi adapter is specific to the country in which it is to be used.

Contact your Bio-Rad Sales representative for the correct adapter to purchase or visit

bio-rad.com/ChemiDocPro and then navigate to Ordering Information > Accessories.

You can connect the ChemiDoc Pro System to internal wireless access points within your organization. When successfully connected, you can access your shared network folder and connect to your BR.io account. ChemiDoc Pro System recognizes all wireless access points within your company and displays the strength and security level of each connection. The imaging system maintains the most recent connection until you change it.

This section explains how to connect the ChemiDoc Pro System to a wireless access point within your organization and how to change wireless connections.

Tip: To set up a shared network folder, see [Configuring the Network Connection](#) [Configuring the Network Connection on page 200](#). To set up a connection to BR.io, see [Linking to Your Bio-Rad BR.io Account](#).


Important: Consult your system administrator for site-specific wireless IP connections and their secure passwords before continuing. Wireless networks that require a captive portal network are not supported.

To connect the ChemiDoc Pro System to a wireless access point


1. Locate your locale-specific ChemiDoc Pro System Wi-Fi adapter and insert it into a USB A port on the imager.

Important: Only use a Bio-Rad Wi-Fi adapter. Other adapters might not be compatible with the ChemiDoc imager.

2. Log into the ChemiDoc Pro System imager as an administrator.
3. Tap Settings in the main toolbar.
4. Tap Network Configuration...



The Network Configuration screen appears. The following image appears if you do not have an Ethernet cable inserted and this is the first time you are setting up a wireless connection.



If your ChemiDoc Pro System is currently connected by Ethernet cable to the network, its connection information appears on the screen:

Network Configuration [Close]

Network Connection: Ethernet

IP Address: 192.168.1.113
 Subnet Mask: 255.255.255.0
 Default Gateway: 192.168.1.1
 MAC Address: 00:30:D6:33:B6:BC
 DNS Servers: 192.168.1.1

[Wi-Fi...] [Ethernet...]

5. Tap Wi-Fi to display a list of available wireless connections.

Wi-Fi [Close]

Only secured Wi-Fi networks are displayed

Wi-Fi Name	Signal Strength (%)	Status
@brlabsecurewpa	66%	Connected
@brVOIP	66%	
@brcorp	66%	
@brlabsecurewpa2	66%	
@brgquest	66%	
@brsecure	66%	

[Force Disconnect] [Refresh] [Disconnect] [Close]

The imager displays the name of each wireless access point and its signal strength:

- Above 75% is considered Strong
- 50–75% is considered Good

- Less than 50% is considered Weak

Tip: If your preferred access point does not appear in the list, click Refresh to refresh the list.

Tip: The list of available networks automatically refreshes when networks are located. If your preferred access point does not appear in the list, or if the list appears empty, tap Cancel to return to the Network Configuration screen and then tap Wi-Fi to return to the Wi-Fi Settings dialog.


6. Tap the preferred access point and then tap Connect.
7. If the preferred access point is secured, you must provide the Wi-Fi password in order to connect.

Note: If you do not know the password, contact your system administrator.

Type the Wi-Fi password then tap OK.

A message appears indicating that the Wi-Fi connection is successful.

8. Tap OK to save the changes.
9. Tap X to close the dialog.
10. The system displays the Wi-Fi icon in the lower left corner of the Welcome screen to indicate successful Wi-Fi connection.




Exporting Log Files

You can export the system log in XML, Text Format, and export the audit log in PDF format. These are independent options. Select either one, or both, in a single export.

Note: If an Administrator account exists, only an Administrator can export log files. If no Administrator account exists, any user can export log files.


To export log files

1. Plug a USB drive into the instrument, or connect to a network.
2. Tap Settings in the main toolbar.
3. Tap Export Logs...



4. In the Export Logs dialog, select one or both of the following:

- **XML, Text Format** — exports the system log
- **PDF** — exports the audit log



5. Do one of the following

- To export to a USB drive, select the USB drive from the list displayed, then tap Send to USB.
- To export to the network, tap Send to Network. Enter the network credentials, then tap Send.

Appendix A Maintaining the Imaging System

Updating the Software and Firmware on ChemiDoc Pro System Imagers

Note: If an Admin user exists on the ChemiDoc Pro System imager, only that user can perform the update. If no Admin user exists, any user can update the system.

The update installer for ChemiDoc Pro System imagers can include software, firmware, and operating system updates. Firmware updates for ChemiDoc Pro System imagers are not distributed in a separate package.

Bio-Rad offers two methods to access and install updates for ChemiDoc Pro System imagers:

- When connected to the Internet, the imager can detect and download updates from the ChemiDoc Pro System product page on bio-rad.com
- You can manually locate and download the updates from the ChemiDoc Pro System product page on bio-rad.com to a USB drive

This section explains how to perform both methods. It also explains how to verify the currently installed software and firmware versions.

Important: Depending on the type of update, the update process can take several minutes.

Verifying the Current Software, Firmware, and Operating Versions

Tip: This section is optional. The update installer checks the current software version and displays the information before continuing the process.

To verify the currently installed version

1. Log on to the ChemiDoc Pro System imager and then tap System Settings on the main toolbar.
2. Tap About This Imager... to display the instrument's information screen, for example:
2026AUG24_Help

Image Lab Touch Software	
© 2026, Bio-Rad Laboratories, Inc.	
Software Version:	0.9.0.13714 CI GC-33c53fa4
Instrument Type:	ChemiDoc Pro
Instrument Name:	ChemiDoc Pro
Serial Number:	ALPHA11
Firmware Version:	1.4.079.1
Camera Serial Number:	ALPHA11
Camera Firmware Version:	1.4.079.1
Disk Image Version:	Bio-Rad ChemiDoc Pro OS Development 0.9.10
BR.io Service Version:	0.9.0.29
Network Connections:	10.2.227.43 (IPv4) fe80::36c9:f0ff:fe90:6f96%wlu1u4 (IPv6)
MAC Address:	34:C9:F0:90:6F:96
Disk Space Free:	93% (869,045 MB)

3. Note the currently installed software version.
4. Tap X to close the system information screen.


Updating the Software and Firmware via the Internet

Note: Before starting the update process, ensure that no image acquisitions or exports are in progress.

To update the software and firmware via the Internet

1. (Optional) Confirm that the ChemiDoc Pro System imager has a network connection:
 - a. If you have not yet done so, log on to the imager and then tap System Settings on the main toolbar.
 - b. Tap About this Imager...
 - c. On the About screen, verify that the Network Connections field lists at least one network connection.
 - d. Close the About screen.
2. On the main toolbar, open System Settings and then tap Update Installation...

The system displays a dialog prompting you to check for an update.




Tip: If you have never checked for updates, Last checked displays Never.

3. Tap Check.

The system checks online for an update.

4. If no update is detected, the system displays a dialog indicating the system is up to date. Tap OK to clear the dialog.
5. If an update is detected, the system displays a dialog prompting you to download the update package.



6. Tap Download.

The system displays a progress bar while the download is in progress.

7. (Optional) Tap Cancel to cancel the process.

Tip: You can restart the download process at any time by performing these steps again.

After the download process completes, the system displays a dialog indicating the current version of the software, the update version, and prompts you to proceed with the update.

8. Tap OK to proceed with the update.
9. To complete the installation, follow the instructions that appear on the touch screen.

Important: Do not interrupt the installation process or turn off the imager while the update is in progress.

Updating the Software and Firmware via USB Drive

Note: Before the installation begins, the system detects the ImageLabTouchSoftware.swu file on the USB drive and displays a message indicating that an update is in preparation. Do not remove the USB drive until the procedure completes.

To update the software and firmware via USB drive


1. Obtain a USB drive and insert it into a USB port on a computer that is connected to the Internet.
Tip: Bio-Rad recommends you use an exFAT or FAT32-formatted drive.
2. Log in to bio-rad.com and navigate to the ChemiDoc Pro System web page.
3. Scroll down to Download and download the ImageLabTouchSoftware.swu file to the root directory of the USB drive.
4. Safely remove the USB drive from the computer.
5. If you have not done so yet, log on to the ChemiDoc Pro System imager.
6. Ensure that no image acquisitions or exports are in progress.
7. Insert the USB drive into the USB port on the imager's panel.
8. If the software version on the USB drive is higher than the software on the instrument, a dialog appears prompting you that an older version has been detected on the instrument.
Tap OK to proceed with the update.
9. To complete the installation, follow the instructions that appear on the touch screen.
Important: Do not interrupt the installation process or turn off the imager while the update is in progress.
10. When the installation completes, you can safely remove the USB drive.

Leveling the Imager


The ChemiDoc Pro System imager should be level to prevent samples from sliding on the sample tray and ensure the best imaging. Place the imager on the surface where you will be using it, and complete the steps below.

To level the imager

1. On the welcome screen, tap the suitcase icon.
2. Tap Level the Imager.



3. Pull out the transilluminator drawer.
4. Place a compatible tray on the transilluminator surface.
Note: The system will generate an error if the tray is not compatible.
5. Retrieve the bubble level included with your instrument accessories.
6. Place the bubble level on the tray, in the middle, as shown in the following graphic.




7. Close the drawer.
8. Tap the green Level the Imager button above. The button turns blue, indicating that the leveling mode is active.

Note: If the button is orange, the drawer is open.

- If the entire bubble is visible inside the level's center ring, the imager is level and no adjustment is needed.
- If the bubble is not centered, adjust the feet as described in step 9, below.

Note: The leveler will close after ten minutes of inactivity.

9. Adjust the level by lifting the imager and rotating the feet until the bubble is centered.
 - To raise the imager, rotate the feet outward.
 - To lower the imager, rotate the feet inward.
 - Adjust each foot until the bubble appears in the center of the ring on the screen.



Each time you adjust the feet you need to acquire a new image to view the new position of the bubble.

10. When the bubble is centered, tap the blue Level the Imager button to exit leveling mode. The button returns to green.
11. Tap outside of the leveling box to return to the welcome screen.

Note: The imager level window times out after ten minutes.

Important: If you move the instrument to a new location, you must repeat this process to level it again.

Cleaning the Instrument

During normal operation, residue can build up on internal and external areas of your ChemiDoc Pro System instrument. On sample trays, residual contamination can affect image data and dust particles can glow under UV illumination.

Use the instructions below to clean the following areas:

- Sample trays
- Transilluminator glass
- Touch screen
- Plastic exterior

To clean the instrument surfaces and accessories

- ▶ Wipe down each surface using a standard laboratory detergent or mild solvent (such as 70% EtOH, MeOH, or IPA).

Important: Note the following:

- For glass areas, use a nonabrasive lint-free towelette.
- Do not clean sample trays in a dishwasher.
- For Coomassie stain, clean until no remaining stain is visible on the towelette.


Preparing the ChemiDoc Pro Imaging System for Shipping

Note: Should you need to return your imager to Bio-Rad, your Bio-Rad Technical Support specialist will provide instructions and packaging material to prepare it for safe return.

Important: Before you begin, ensure that you have completely exported images to BR.io or to a network or USB drive.

To prepare the imager for shipping

1. On the Welcome screen, tap the suitcase icon.
2. Tap Prepare the Instrument for Shipping. The camera moves to the halfway position.
3. Open the drawer and remove the tray.
4. Tap OK. The camera moves into shipping position.
5. Place the narrow end of the foam wedge into the imager with the foam flat on the transilluminator and the pads facing up.
6. Close the drawer.
7. Tap OK. The camera moves into the lowered shipping position.
8. Press the Power button to turn off the imager.
9. Unplug the AC power cord from the back of the imager.
10. Repackage the instrument according to the shipping instructions.



Maintaining the LED Lamps

Note: The ChemiDoc Pro System imager uses custom LED lamps as the illumination source, which are designed to last the life of the instrument. The LED lamps are not serviceable or replaceable by the customer.

Replacing the Fuses

Replace the fuse with the following acceptable replacement fuse:

Name	Number	Voltage	Description
Schurter	0034.3124	250VAC	250V, 5A, 5 x 20 mm

To replace the ChemiDoc Pro System fuses

1. Unplug the power cord from the back of the instrument.
2. Using a small flathead screwdriver, insert the tip to loosen the black fuse box cover.



3. Pull out the red fuse box.



4. Pull out the fuse box and gently pop out the fuse.



5. Press the fuse box into place.


Exporting Log Files

You can export the system log in XML, Text Format, and export the audit log in PDF format. These are independent options. Select either one, or both, in a single export.

Note: If an Administrator account exists, only an Administrator can export log files. If no Administrator account exists, any user can export log files.


To export log files

1. Plug a USB drive into the instrument, or connect to a network.
2. Tap Settings in the main toolbar.
3. Tap Export Logs...



4. In the Export Logs dialog, select one or both of the following:

- **XML, Text Format** — exports the system log
- **PDF** — exports the audit log



5. Do one of the following

- To export to a USB drive, select the USB drive from the list displayed, then tap Send to USB.
- To export to the network, tap Send to Network. Enter the network credentials, then tap Send.

Appendix B Important Imaging Concepts

This appendix provides additional information on important concepts for working with the ChemiDoc Pro System imager.

Exposure Settings for Chemiluminescent Applications


You can use the Image Resolution/Time scale with adjustable binning settings to optimize the image you want to acquire. Choose a lower binning setting (higher resolution) for higher-quality images. If bands are faint, choose a higher binning setting for a shorter exposure time and the degree of sensitivity you require.

Image Lab Touch Software automatically determines the optimal setting required to achieve images suitable for quantitation or publication, as indicated by the Image Resolution/Time Scale. Images acquired at the optimal setting have a resolution of 175 microns or more per pixel. Selecting lower bin settings increases the resolution but might also increase the imaging time. Selecting higher bin settings reduces the resolution and exposure time but might result in a lower resolution than required.

Bio-Rad recommends that you start with the optimal binning setting shown in the Image Resolution/Time Scale, examine the result, and adjust the setting for subsequent images.

The Image Resolution/Time Scale

The Image Resolution/Time scale includes six pixel resolution settings: 1x1, 2x2, 3x3, 4x4, 6x6, and 8x8. The optimal binning setting required to achieve high-quality images is indicated by a check mark on the Image Resolution/Time scale.




LEGEND

	Binning level
	Selected binning setting
	Optimal binning setting

Tap a different binning setting on the Image Resolution/Time scale to change the binning level.

When selecting acquisition options, you can view the selected binning setting under Exposure in the imaging settings tile, for example:



Selected binning

How Binning Settings Affect Image Quality

Pixel binning refers to the process of combining data from adjacent CMOS pixels to form a single larger pixel. Doing so results in faster acquisition speeds and, in most images, improved light sensitivity. However, pixel binning is achieved at the cost of reduced resolution. A binning of 2x2 means that 4 adjacent pixels are combined into one larger pixel. A binning of 3x3 means that 9 pixels are combined into one, 4x4 means that 16 are combined into one, and so on.

Pixel binning combines adjacent pixels into a single larger pixel:

Binning option	Combined pixels on the CCD chip
None	
2x2 (4 pixels = 1)	
3x3 (9 pixels = 1)	
4x4 (16 pixels = 1)	
6x6 (36 pixels = 1)	

Using pixel binning, you can balance resolution and exposure time to acquire an image with the sensitivity best suited for your purposes:

- **Sensitivity** — as binning increases, sensitivity to light increases in most images, which improves the ability of the camera to detect faint bands. A binning of 4x4 uses 16 pixels compared to a binning of 2x2, which uses four pixels. As a result, a binning of 4x4 is four times more sensitive than a binning of 2x2.

Note: At higher binning settings, sensitivity might depend on the signal intensity and size of the feature being imaged relative to the background. If the bin contains more pixels than the feature (for example, a band), the intensity is averaged over the binned area. In some images, a higher binning setting might render the feature not visible above the background.

- **Resolution** — resolution decreases at all binning settings greater than 2x2. As pixel binning increases, fewer pixels appear in the resulting image. As a result, resolution decreases more noticeably at higher binning settings.
- **Exposure time** — as pixel binning increases, it takes less time to acquire the image because larger pixels collect more light. In addition, faster acquisition times accumulate less instrument background which might improve visualization of faint bands.


Tip: Zooming in on the area to be imaged increases the resolution and might increase the optimal binning. The loss in resolution with a higher binning setting can be offset by the smaller imaging area and result in a shorter exposure time.

In general, a 3x3 binning setting produces an image that is relatively higher in resolution and requires longer exposure times to achieve equivalent sensitivity to a higher binning setting. An 8x8 binning setting usually produces an image that is relatively lower in resolution, higher in sensitivity (faint bands are optimized), and takes less exposure time to produce.


Tip: For a first acquisition of a sample, you might use a higher binning setting (for example, 6x6) with a shorter exposure time. Evaluate the results and then use a 3x3 binning setting with a longer exposure time on the next acquisition. With some acquisitions the 2x2 binning setting might produce an image with optimal resolution and acceptable sensitivity.

The two gel lanes above the binning setting show how an image looks given the selected setting. As you tap the binning settings change, the image displayed changes to show the relationship between the resolution and sensitivity.

More intense bands with higher resolution appear at lower binning settings, for example:



At higher binning settings, faint bands appear more prominent but resolution is reduced, for example:



Specifying the Region of Interest for Optimal Exposure

Preview displays a low-resolution image of the sample. When you select an automatic exposure setting, you can use the preview image to specify the region of interest by surrounding bands or other features with a selection rectangle.

Image Lab Touch Software acquires the entire image and sets the automatic exposure so that the brightest pixels in the region of interest are exposed to near saturation and the rest of the image is exposed to show as much dynamic range as possible. Specifying a region of interest is especially valuable when you are setting automatic exposure for chemiluminescent or fluorescent samples.

Try specifying the region of interest for the following purposes:

- To evaluate relative signal intensities, all features that you want to compare must be unsaturated. To prevent saturation of features, specify a region of the blot encompassing the area of interest.
- To push the limits of sensitivity, specify a region of faint or no apparent signal. The software optimizes the exposure to reveal features in the specified region, but might cause saturation of more intense features on the blot.

Adjusting How Images Are Displayed

Image Lab Touch Software optimizes images based on the range of intensity levels in the image and the known behavior of the applications. Use this optimized image as a starting point. Use the histogram scale and the grayscale curve settings in the Transform dialog to adjust the image brightness and contrast as necessary.

Important: The transform settings change only the *appearance* of the image, not the underlying data.

Note: Chemiluminescent images taken in SAM mode are displayed with a fixed transform so you can compare them. The intensity is set to the bottom third of the full range, and the gamma is set to .75. The fixed transform enables you to distinguish accurately the differences between the images in one SAM acquisition so you can select the best one.

Adjusting Image Brightness and Contrast

Transform adjusts image brightness and contrast, optimizing the image display to highlight features of interest. The minimum to maximum range varies depending on the light and dark values present in the image. Adjustments to brightness and contrast do not change the data. They change only the way the data are displayed.

The frequency distribution histogram shows the total data range in the image and the amount of data at each point in the range. The lightest part of the image is set to the minimum intensity, and the darkest is set to the maximum.

Use the Low and High sliders to narrow the displayed grayscale range.


- The High indicator determines the intensity value shown at the maximum value of the grayscale in the gel image.
- The Low indicator determines the intensity value shown at the minimum value of the grayscale in the gel image.
- The Gamma slider changes the grayscale curve. A value of 1 is linear. A value of <1 redistributes more of the grayscale to the first half of the intensity values. A value of >1 redistributes more of the grayscale to the second half of the intensity values.

A logarithmic histogram can reveal the presence of intensity values that are otherwise obscured. In images with a large background area, the intensity value of most pixels is that of the background. Often, there are too few pixels at the intensity values of the data peaks of interest to make these peaks readily visible in a linear histogram.

A linear histogram can be useful when intensity values are more evenly distributed. Used in combination with the logarithmic histogram, the linear histogram shows more clearly the relative quantity of pixels at each intensity value.

To change the histogram scale

1. Open an image in Image View and tap Transform.
2. Tap the Log Histogram box to choose the logarithmic scale.




To change the light intensity range displayed in the image

- Tap and drag the Low or High slider.
 - Drag the Low slider to the right to obscure the background and low-intensity bands and to make high-intensity bands more visible.
 - Drag the High slider to the left to make the background, nonspecific binding, and low-intensity bands more visible. Intense bands might look overexposed.

To adjust the grayscale curve

- ▶ Tap and drag the Gamma slider or touch anywhere in the slider bar.



Other Display Options


- **Zoom in and out** — displays greater detail about the intensity range.
- **Highlight saturated pixels** — pixels with saturated signal (higher than a measurable range) are displayed as red areas.
- **Invert image display** — inverts dark and light areas. Clear the box to return to original display.

Restoring Default Settings

After changing the brightness and contrast settings for an image, you can restore the default settings.

To restore default settings

- ▶ Tap Auto.



(Single Channel) Signal Accumulation Mode

Signal Accumulation Mode (SAM) is a semi-automated alternative for acquiring chemiluminescent images. Rather than taking a series of single images with different exposure settings, SAM produces a series of cumulative images. Each successive image includes all of the accumulated signal of the previous images, plus additional exposure time.

To calculate the SAM exposure setting, estimate the shortest and the longest exposure times you think will achieve the optimal image. Decide on the total number of images to be taken within this time range. For example, assume you want to take four images. You specify a minimum exposure time of 60 seconds and a maximum of 240 seconds. The first image is taken at 60 seconds, the last image is taken at 240 seconds, and the remaining two images are taken at even intervals in between, at 120 and 180 seconds.

SAM is useful for determining the optimal imaging time for a chemiluminescent sample. However, signals near the intensity of background noise become less visible with each successive image. After you have used SAM to determine the optimal exposure time, acquire a single image of the sample using the optimal exposure to identify very faint signals in the image.

Appendix C Application Emission Filter and Excitation Source Information

The table below lists the excitation source values and emission filters for each default application.

Note: An asterisk next to a tray for an application identifies it as the recommended tray for the application.

Table 18. Application Emission Filter and Excitation Source Information.

Emission Filter and Excitation Source	Application	Tray
■ Emission Filter: 511/252 ■ Source: No light	Chemiluminescence	Blot
	Alexa 488	Blot
	Cy2	Blot
■ Emission Filter: 532/28 ■ Excitation Source: Blue Epi	DyLight 488	Blot
	Fluorescein (Blot Membrane)	Blot
	StarBright B520	Blot
	Pro-Q Emerald 488	Blue

Table 18. Application Emission Filter and Excitation Source Information., continued

Emission Filter and Excitation Source	Application	Tray
■ Emission Filter: 590/110 ■ Excitation Source: Blue Trans	Coomassie Fluor Orange	Blue
	Diamond	Blue*
	Flamingo	Blue
	Fluorescein (Gel)	Blue
	GelGreen	Blue*
	GelStar	Blue*
	SYBR Gold	Blue*
	SYBR Green	Blue*
	SYBR Safe	Blue*
■ Emission Filter: 590/110 ■ Excitation Source: UV Epi	Stain-Free (Blot Membrane)	Blot
	SYPRO Ruby (Blot Membrane)	Blot

Table 18. Application Emission Filter and Excitation Source Information., continued

Emission Filter and Excitation Source	Application	Tray
■ Emission Filter: 590/110 ■ Excitation Source: UV Trans	Diamond	UV/Stain-Free
	Ethidium Bromide	UV/Stain-Free
	Flamingo	UV/Stain-Free*
	GelGreen	UV/Stain-Free
	GelRed	UV/Stain-Free
	GelStar	UV/Stain-Free
	OliGreen	UV/Stain-Free
	Oriole	UV/Stain-Free*
	PicoGreen	UV/Stain-Free
	Pro-Q Emerald 300	UV/Stain-Free
	Stain-Free (Gel)	UV/Stain-Free
	SYBR Gold	UV/Stain-Free
	SYBR Green	UV/Stain-Free
	SYBR Safe	UV/Stain-Free
	SYPRO Ruby (Gel)	UV/Stain-Free
	UView	UV/Stain-Free
■ Emission Filter: 590/110 ■ Excitation Source: White Epi	Amido Black	Blot
	Colorimetric	Blot
	Copper Stain	Blot
	Ponceau S	Blot
■ Emission Filter: 590/110 ■ Excitation Source: White Epi	Zinc Stain	Blot

Table 18. Application Emission Filter and Excitation Source Information., continued

Emission Filter and Excitation Source	Application	Tray
■ Emission Filter: 590/110 ■ Excitation Source: White Trans	Coomassie Blue	White
	FastBlast	White
	Silver Stain	White
■ Emission Filter: 595/36 ■ Excitation Source: Green Epi	Alexa 546	Blot
	Cy3	Blot
	Dylight 550	Blot
	Krypton	Blot
	Pro-Q Diamond	Blot
	Rhodamine	Blot
■ Emission Filter: 700/50 ■ Excitation Source: Red Epi	Alexa 647	Blot
	Cy5	Blot
	DyLight 650	Blot
■ Emission Filter: 715/30 ■ Excitation Source: Blue Epi	StarBright B700	Blot
■ Emission Filter: 715/30 ■ Excitation Source: Far Red Epi	Alexa 680	Blot
	Coomassie Blue	White
	Cy5.5	Blot
	DyLight 680	Blot
	IR Dye 680RD	Blot
■ Emission Filter: 836/47 ■ Excitation Source: IR Epi	Alexa 790	Blot

Table 18. Application Emission Filter and Excitation Source Information., continued

Emission Filter and Excitation Source	Application	Tray
■ Emission Filter: 836/47 ■ Excitation Source: IR Epi	Cy7	Blot
	DyLight 800	Blot
	IR Dye 800CW	Blot
* Recommended tray for the application		

Appendix D Free and Open-Source Notices for ChemiDoc Pro Imaging Systems

Bio-Rad's ChemiDoc Pro Imaging System products are developed using and incorporate or are bundled with third-party materials (together, the "MATERIALS") subject to free, open-source, or public-source licenses (each an "OPEN LICENSE"). The terms of applicable OPEN LICENSES govern Bio-Rad's distribution and your use of the MATERIALS. Bio-Rad and the third-party authors, licensors, and distributors of the MATERIALS disclaim all warranties and liability arising from all use and distribution of the MATERIALS. To the extent the MATERIALS are provided under an agreement with Bio-Rad that differs from the applicable OPEN LICENSES, those terms are offered by Bio-Rad alone.

The source code for MATERIALS included with ChemiDoc Pro System products may be downloaded from <http://bio-rad.com/ChemiDocPro-opensource>. The downloadable source code retains all copyright and other licensing notices originally included within the MATERIALS. Additionally, the reported license terms for the MATERIALS are available via the Legal Notices link provided on the System tile on the ChemiDoc Pro System's About screen.

While Bio-Rad seeks to provide complete and accurate copyright and licensing information for all MATERIALS, Bio-Rad does not represent or warrant that the copyright or licensing information is complete, correct, or error-free. MATERIALS recipients are encouraged to (a) investigate the identified MATERIALS to confirm the accuracy of the licensing information provided and (b) notify Bio-Rad of any inaccuracies or errors found in this document so that Bio-Rad may update this notice and the downloadable source code accordingly.

Viewing the OSS License Text

To view the OPEN LICENSE text

- On the ChemiDoc Pro Imaging System, navigate to Tools > About and tap Legal Notices on the System tile.

Downloading the Open Sources Software

To download the open source software

- In a web browser, navigate to <http://bio-rad.com/ChemiDocPro-opensource>

Appendix E Ordering Information

Catalog #	Description
Imaging Systems	
17011351	ChemiDoc Pro Imaging System with Image Lab Touch Software
Analysis Software	
12012931	Image Lab Software on a USB drive
17006130	Image Lab Software, Security Edition, 1 license on a USB drive
17006171	Image Lab Software, Security Edition, 5 licenses on a USB drive
17006172	Image Lab Software, Security Edition, 10 licenses on a USB drive
ChemiDoc Pro Imaging System Trays	
12019873	White Tray
12019748	Blue Tray
12012189	UV/Stain-Free Tray
12026421	Blot Tray
Optional Accessories	
12012164	UV Safety Shield for ChemiDoc Pro System Imaging System
1708377	Holder for Sample Trays and UV Shield
1708185	XcitaBlue Viewing Goggles
12012190	ChemiDoc Pro System Gel Alignment Kit
1703759	Bio-Rad Fluorescent Ruler
12019757	ChemiDoc Pro System Imaging System IQ/OQ Kit

Catalog #	Description
■ 12018650 (United States)	Wi-Fi adapter for use with ChemiDoc Go and ChemiDoc Pro imaging systems Contact your Bio-Rad Sales representative for information about the adapter specific to your locale.
■ 12018509 (Global)	
Electrophoresis Cells	
1656001	Criterion Cell, includes vertical midi-format electrophoresis cell, buffer tank, lid with power cables, 3 sample loading guides
1658004	Mini-PROTEAN Tetra Cell for Mini Precast Gels, 4-gel vertical electrophoresis system, includes electrode assembly, companion running module, tank, lid with power cables, mini cell buffer dam
Nucleic Acid Standards	
1708351	EZ Load 20 Base Pair Molecular Ruler
1708352	EZ Load 100 Base Pair Molecular Ruler, 500 µl, 100 applications
1708353	EZ Load 100 Base Pair PCR Molecular Ruler, 500 µl, 100 applications
Protein Standards	
1610373	Precision Plus Protein All Blue Standards, 500 µl, 50 applications
1610363	Precision Plus Protein Unstained Standards, 1 mL, 100 applications
1610374	Precision Plus Dual Color Standards, 500 µl, 50 applications
1610376	Precision Plus Protein WesternC Blotting Standards, 250 µl, 50 applications
Buffers	
1610732	10x Tris/Glycine/SDS, 1L
1610743	50x, TAE (Tris Acetic Acid/EDTA) Buffer, 1L
1610747	4x Laemmli Sample Buffer, 10 mL
Blotting Systems	

Catalog #	Description
1704150	Trans-Blot Turbo Starter System, blotting instrument, includes base, 2 cassettes to hold 1 or 2 midi or up to 4 mini blotting sandwiches, blot roller
1703940	Trans-Blot SD Semi-Dry Electrophoretic Transfer Cell, semi-dry electrophoretic transfer cell, includes agarose gel support frame, extra thick blot paper in 4 sheet sizes
1703930	Mini Trans-Blot Electrophoretic Transfer Cell, gel transfer cell, for two 10 x 7.5 cm gels, includes 2 gel holder cassettes, foam pads, electrodes, tank, blue cooling unit, lid with cables
1704156	Trans-Blot Turbo Transfer Pack, mini, PVDF, pkg of 10
1704157	Trans-Blot Turbo Transfer Pack, midi, PVDF, pkg of 10
1704158	Trans-Blot Turbo Transfer Pack, mini, nitrocellulose, pkg of 10
1704159	Trans-Blot Turbo, Transfer Pack, midi, nitrocellulose, pkg of 10
1704270	Trans-Blot Turbo, RTA Transfer Kit, mini, nitrocellulose
1704271	Trans-Blot Turbo, RTA Transfer Kit, midi, nitrocellulose
1704272	Trans-Blot Turbo, RTA Transfer Kit, mini, PVDF
1704273	Trans-Blot Turbo, RTA Transfer Kit, midi, PVDF
1704274	Trans-Blot Turbo, RTA Transfer Kit, mini, LF PVDF
1704275	Trans-Blot Turbo, RTA Transfer Kit, midi, LF PVDF
Detection Reagents	
1705060	Clarity ECL Substrate, 200 mL, 25 blots
1705062	Clarity Max ECL Substrate, 100 mL, 15 blots



Bio-Rad and ChemiDoc are trademarks of Bio-Rad Laboratories, Inc. in certain jurisdictions.
All trademarks used herein are the property of their respective owner. © 2026 Bio-Rad Laboratories, Inc.



Bio-Rad
Laboratories, Inc.

Life Science
Group

Website [bio-rad.com](https://www.bio-rad.com) USA 1 800 424 6723 Australia 61 2 9914 2800 Austria 00 800 00 24 67 23 Belgium 00 800 00 24 67 23 Brazil 55 11 3065 7550
Canada 1 800 361 1808 China 86 21 6169 8500 Czech Republic 00 800 00 24 67 23 Denmark 00 800 00 24 67 23 Finland 00 800 00 24 67 23
France 00 800 00 24 67 23 Germany 00 800 00 24 67 23 Greece 30 210 7774396 Hong Kong 852 2789 3300 Hungary 00 800 00 24 67 23
India 91 124 4029300 Israel 000 800 00 24 67 23 Italy 00 800 00 24 67 23 Japan 81 3 6361 7000 Korea 82 080 007 7373 Luxembourg 00 800 00 24 67 23
Mexico 52 55 5488 7670 The Netherlands 00 800 00 24 67 23 New Zealand 64 9 415 2280 Norway 00 800 00 24 67 23 Poland 00 800 00 24 67 23
Portugal 00 800 00 24 67 23 Russian Federation 7 495 721 14 04 Singapore 65 6415-3170 South Africa 27 21 531 7504 Spain 00 800 00 24 67 23
Sweden 00 800 00 24 67 23 Switzerland 00 800 00 24 67 23 Taiwan 886 2 2578 7189 Thailand 662 651 8311 United Arab Emirates 971 4 818 7300
United Kingdom 00 800 00 24 67 23